

Received April 28, 2020, accepted May 15, 2020, date of publication May 21, 2020, date of current version June 9, 2020.

Digital Object Identifier 10.1109/ACCESS.2020.2996177

Overview of H -Formulation: A Versatile Tool for Modeling Electromagnetics in High-Temperature Superconductor Applications

BOYANG SHEN¹, (Member, IEEE), FRANCESCO GRILLI²,
AND TIM COOMBS¹, (Senior Member, IEEE)

¹Electrical Engineering Division, Department of Engineering, University of Cambridge, Cambridge CB3 0FA, U.K.

²Institute for Technical Physics, Karlsruhe Institute of Technology (KIT), 76131 Karlsruhe, Germany

Corresponding author: Francesco Grilli (francesco.grilli@kit.edu)

ABSTRACT This paper reviews the modeling of high-temperature superconductors (HTS) using the finite-element method (FEM) based on the H -formulation of Maxwell's equations. This formulation has become the most popular numerical modeling method for simulating the electromagnetic behavior of HTS, especially thanks to the easiness of implementation in the commercial finite-element program COMSOL Multiphysics. Numerous studies prove that the H -formulation is able to simulate a wide scope of HTS topologies, from simple geometries such as HTS tapes and coils, to more complex HTS devices, up to large superconducting magnets. In this paper, we review the basics of the H -formulation, its evolution from 2D to 3D, its application for calculating critical currents and AC losses as well as magnetization of HTS bulks and tape stacks. We also review the use of the H -formulation for large-scale HTS applications, its use to solve multi-physics problems involving electromagnetic-thermal and electromagnetic-mechanical couplings, and its application to study the dynamic resistance of superconductors and flux pumps.

INDEX TERMS Review, H -formulation, high temperature superconductor (HTS), finite-element method (FEM).

I. INTRODUCTION

In recent years, the electromagnetic and mechanical performance of high-temperature superconductors (HTS) has remarkably increased. The high current density and the possibility of cryogen-free operation make HTS the most suitable candidate for future superconducting applications [1]. Another advantage of HTS is that their price has been gradually decreasing [2]. All these reasons make HTS a technically and economically viable solution for various superconducting applications [3]–[18], and some of such applications have almost reached the market. While the price of HTS is still too high to compete with well-established conventional applications such as power cables and transformers, certain HTS applications are already well established: resistive superconducting fault current limiters are at a pre-commercial stage and HTS magnets have reached record-breaking magnetic fields.

The associate editor coordinating the review of this manuscript and approving it for publication was Derek Abbott¹.

Meanwhile, the investigation and research of HTS have also developed from simple objects to more complex devices and to large-scale applications. For simulating the behavior of complex HTS systems, analytical solutions are not accurate, and experimental investigations can be challenging, time consuming, and even risky. Therefore, numerical tools are becoming increasingly important to design HTS applications and predict their performance.

For the simulation of the electromagnetic behavior of HTS, several numerical models based on different formulations, such as A - V [19], T - Ω [20], T - A [21], and H -formulation [22]–[24] have been proposed. In 2003, the H -formulation, which takes its name from the single dependent variable of magnetic field intensity H , was first used to calculate macroscopic current and field distributions in superconductors in home-made codes [22], [25] and successively implemented in the commercial finite-element method (FEM) software COMSOL Multiphysics by Hong *et al* [23] and Brambilla *et al* [24]. The H -formulation has been widely used for modeling various HTS topologies, with the advantages of accuracy, good convergence and acceptable

computing time. Based on the citations of the two papers [23], [24] mentioned above and on presentations at technical conferences, we have identified more than 45 research groups worldwide using the \mathbf{H} -formulation for modeling the electromagnetic behavior of superconductors.

This paper overviews the previous works on HTS with the \mathbf{H} -formulation FEM models, starting from the basics of the \mathbf{H} -formulation, and covering its evolution from 2D to 3D, its application for calculating critical currents and AC losses and for investigating the magnetization of HTS bulks and tape stacks. Reviewed here is also the use of the \mathbf{H} -formulation for large-scale HTS applications, its use for solving multi-physics problems involving electromagnetic-thermal and electromagnetic-mechanical couplings, and its application for studying the dynamic resistance of superconductors and flux pumps. A schematic illustration of some of the possible uses of the \mathbf{H} -formulation is given in Figure 1. This review can be helpful for researchers to understand the mechanism, development, and scope of applications of the \mathbf{H} -formulation FEM model for HTS, which could be beneficial for the future designs of HTS applications.

II. BASICS OF THE H-FORMULATION

From the mathematical point of view, the \mathbf{H} -formulation uses the finite-element method to solve Faraday's equation:

$$\nabla \times \mathbf{E} = -\frac{\partial \mathbf{B}}{\partial t} \quad (1)$$

using the magnetic field \mathbf{H} as state variable and a nonlinear resistivity for describing the peculiar electrical characteristics of superconductors:

$$\rho = \frac{E_0}{J_c} \left| \frac{\mathbf{J}}{J_c} \right|^{n-1} \quad (2)$$

where E_0 is a characteristic electric field (generally 10^{-4} V/m), \mathbf{J} is the current density, J_c is the critical current density and n is a factor indicating the steepness of the transition from the superconducting to the normal state. This power-law model for the superconductor material approaches Bean's critical state model as the power law factor n increases toward infinity [26]. The power-law is commonly used because it describes the power dissipation typically occurring at power frequencies. For slower phenomena (e.g. relaxation), the percolation-law could give a more precise description [27], [28]. The non-conducting regions are modelled as materials with high resistivity. A resistivity value of $1 \Omega \cdot \text{m}$ is often used: it is sufficiently large, thus avoiding the flow of current in non-conducting regions, and it does not excessively increase the computation time.

From the magnetic point of view, the superconductor is modelled as a material with relative magnetic permeability $\mu_r = 1$. Faraday's equation expressed in terms of magnetic field takes the form:

$$\frac{\partial (\mu_0 \mu_r \mathbf{H})}{\partial t} + \nabla \times (\rho \nabla \times \mathbf{H}) = 0 \quad (3)$$

The zero-divergence of the magnetic flux density is guaranteed by the choice of zero initial conditions, as explained in [29]. The current density \mathbf{J} is derived from the magnetic field by means the quasi-static approximation of Ampere's law:

$$\nabla \times \mathbf{H} = \mathbf{J} \quad (4)$$

Equation (3) can be solved by FEM software programs such as COMSOL Multiphysics [24], Matlab [30], FlexPDE [31], home-made FEM codes such as Daryl Maxwell [32], and open-source environments such as GetDP [33].

III. EVOLUTION FROM 2D TO 3D

The early studies based on the \mathbf{H} -formulation mostly employed two-dimensional models, simulating the transverse cross section of long superconductors with the current flowing perpendicular to the cross section. In such models, the magnetic field has only two components (in the plane of the analyzed cross section) and the current density has only one component, in the direction perpendicular to the field. Those early models were used to calculate AC losses and were successfully validated against experimental measurements and analytical solutions [23], [24], [34], [35].

The challenge of simulating superconductors with very large width-to-thickness ratio (such as HTS coated conductors) was first tackled by artificially expanding the superconducting layer's thickness [36] and then, for systems characterized by a large number of tapes, with the homogenization method [37]. In addition, Rodriguez-Zermeno *et al* developed a useful way to reduce the number of degrees of freedom using a structured and elongated rectangular mesh [38], which allowed accurately simulating the superconducting layer with its real thickness and saving computation time.

The \mathbf{H} -formulation was then extended to 3D, in order to handle problems of increasing complexity. In general, the equations are the same, and it is assumed that the current density is parallel to the electric field – an assumption that is not necessarily true in three dimensions. In addition, in the majority of cases, it is assumed that the resistivity given by equation (2) is isotropic.

In [39], Zhang *et al* built 3D \mathbf{H} -formulation FEM models for HTS bulks and HTS tapes, and calculated their electromagnetic profiles in order to estimate the AC losses. In [40], a full 3D model of superconducting twisted wires transporting AC electric current was established. In the same work, the 3D model was also used to analyze the influence of material defects in HTS tapes. In [29], Zermeno *et al* built a full 3D model of a Roebel cable made of 14 strands, and they did a comprehensive investigation on current distributions and AC losses: they found that a significant advantage of the 3D model over its 2D counterpart was the capability of revealing the presence of small highly dissipative regions near the corners of Roebel cable. In [41], a full 3D model of a race-track HTS coil was built with the homogenization approach and compared to 2D models. Two-dimensional axisymmetric \mathbf{H} -formulation FEM models were also developed [42]–[44].




FIGURE 1. Scope of the applications of *H*-formulation: AC loss calculation, critical current and DC characteristics, HTS bulks and stacks magnetization, large-scale HTS applications, electromagnetic-thermal and electromagnetic-mechanical coupled problems, dynamic resistance and flux pump.

IV. AC LOSS CALCULATION

AC losses can constitute a serious refrigeration burden, limiting the efficiency and increasing the operational cost of superconducting applications. Their estimation is therefore very important. AC losses in HTS tapes and coils can be measured with different experimental techniques, such as the electrical method [45], the magnetic method [46], and the calorimetric (boil off) method [46]. However, the measurements require dedicated experiments, which are often delicate and lengthy. In addition, AC loss measurements become much more challenging with large-scale superconducting applications. Therefore, reliable tools which are able to accurately estimate the AC loss values of superconducting devices are particularly sought for.

In the past decades, several analytical models for the calculation of AC losses in superconductors have been developed. These models provide close-form expressions for the AC losses as a function of few physical and geometrical parameters. Among the most used ones are the expressions by Norris [47] and Brandt [48] for the transport and magnetization losses in individual superconductors with simple geometry (such as infinitely long tapes and wires with elliptical or thin rectangular cross section). A comprehensive review of available analytical models is given in [49]. Analytical models are efficient for computing the losses of simple geometries of HTS, but in general they cannot be used for large-scale superconducting devices. By contrast, numerical models can model geometries and situations of increasing complexity. One of the main advantages of the *H*-formulation FEM model is its accurate AC loss computation for various HTS topolo-

gies under the actions of different current and magnetic field conditions.

Currently, the most widely used HTS tapes are rare-earth barium copper oxide (REBCO) coated conductors. They consist of different layers: the superconducting layer (which is extremely thin, typically 1 μm), the encapsulation, the stabilizer, and the substrate. In general, there are four types of losses that possibly contribute to the total AC loss of a REBCO HTS tape [50]:

- hysteresis losses, in the superconducting material;
- coupling losses, when tapes are subdivided into filaments;
- magnetic losses, if there are magnetic materials;
- eddy-current losses, in the metals.

In most cases of practical interest, the hysteresis losses in the superconducting material dominate, if the frequency of the AC excitation is not too high (e.g. less than 1 kHz) and there are no magnetic materials or filaments. The *H*-formulation is primarily used for calculating the hysteresis losses, but the other types of losses can also be calculated [50]. In the *H*-formulation model, the AC loss can be calculated by integrating the instantaneous power dissipation over the domain of interest (the superconductor or the metal) and taking the average over a cycle [51]–[53]:

$$Q = \frac{1}{T} \int_T \int_{\Omega} \mathbf{E} \cdot \mathbf{J} \, d\Omega dt \quad (5)$$

where T is the time interval of each cycle of AC signal, and Ω is the domain for loss calculation. For the purpose of more accurate loss results, various versions of *B*-dependent




FIGURE 2. Comparison of the H -formulation FEM model, measurement, and analytical solutions (Norris ellipse and Norris strip), for the analysis of the AC loss from a HTS a single tape and double pancake coil, with transport current at 50 Hz, with data from [56].

critical current models are usually incorporated into the H -formulation [54], [55].

Figure 2 shows results for the AC losses of a single HTS tape and a double pancake HTS coil fabricated with the same material (SCS6050 from SuperPower), with a 50 Hz AC transport current [56]. The AC losses calculated with the H -formulation for both single tape and coil agree with the experiments on a wide range of values (more than four orders of magnitude).

The H -formulation can calculate the losses from the different materials of REBCO HTS tapes, such as the magnetic AC losses in the magnetic substrates, and the eddy-current AC losses in the metals (e.g. copper stabilizer and silver over-layer). Nguyen *et al* used a modified version of the H -formulation with a non-linear magnetic permeability to calculate the total AC losses in the HTS tapes with magnetic substrates [57]. Shen *et al* used the H -formulation model to compute the eddy-current AC losses in the copper stabilizer, and the overall AC losses in the HTS tapes (SuperPower, SCS12050 and SF12100). The results were verified by the measurements [58].

The H -formulation can be used to calculate the electromagnetic interaction and the AC losses of tapes when they are assembled in the form of vertical stacks or horizontal arrays. The magnetization AC losses of a vertical stack of HTS tapes were studied in [34], with a good match between the simulation results and the experimental values. Shen *et al* carried out experiments and simulations for the AC losses in an horizontal array of HTS tapes and predicted the AC losses with increasing numbers of tapes in the array [51].

Several studies have been dedicated to the calculation of AC losses by means of the H -formulation. Hong *et al* modelled the magnetization losses of a superconducting racetrack coil with the conditions of ripple field together with DC background field or DC transport current [59]. Xu and Grilli investigated the AC losses in a 4-mm HTS tape in the presence of various DC and AC ripple currents [60]. Lahtinen *et al*

simulated ripple field losses under the action of direct current and varying magnetic field, finding a good agreement with experiments in most of the considered cases [61]. In general, care should be taken for evaluating AC ripple losses [62]. The H -formulation uses a power-law resistivity (see equation (2)), which causes a relaxation of the current density distribution associated to the DC component. The value of the cyclic AC ripple losses calculated by means of equation (5) depends on when the calculation is performed along such relaxation. Usually one has to wait until the relaxation of the DC component does not influence the results. This usually requires simulating a large number of cycles.

Nguyen *et al* carried out an AC loss study on anti-parallel connected HTS tapes, which is a beneficial configuration for superconducting fault current limiter applications [63]. A method to reduce AC losses of HTS tapes is by striating the tape into a large number of filaments and narrow grooves: the efficiency of this method was demonstrated with experiments and confirmed by FEM simulations in [64]. Grilli *et al* used the H -formulation to carry out the numerical modeling and loss analysis of a twisted stacked tape cable (TSTC) [65]. The possibility of considering the effect of contact resistances on the current distributions in HTS cables was introduced in [66].

The H -formulation FEM model can be a useful tool to simulate various configurations of HTS cables, such as the Roebel cable, conductor-on-round-core (CORC) cable, and other ones. In [67], Grilli and Pardo calculated the AC losses of Roebel cables, and their study provided insights on the losses for the cases of coupled and uncoupled HTS strands. Several AC loss studies on Roebel cables were performed by means of both experiments and simulations based on the H -formulation (both 2D and 3D) with different conditions of transport current and magnetic field [29], [68]–[71]. Majoros *et al* and Terzio lu *et al* investigated the magnetization and transport AC losses of HTS CORC by experiments and simulations [72], [73]. There are other types of HTS cables, such as the twisted stacked tape (TSTC) HTS wires, soldered-stacked-square-twisted (3S-T) HTS cable, quasi-isotropic strands, HTS Cross-Conductor Cables, whose AC loss characteristics have been studied by using the H -formulation [65], [74]–[76].

Quéval *et al* used the H -formulation to calculate the AC loss of large-scale HTS coated conductor applications. Their work also included the comparison of a full model (simulating all the turns of a large coil) with multi-scale and homogenized models [77]. These last two models – presented in more detail in Section VII – allow dramatically reducing the size of the problem and the computation time, without significant loss of accuracy.

A systematic review of the AC loss computation for HTS using the H -formulation is presented in [78].

V. CRITICAL CURRENT AND DC CHARACTERISTICS

The H -formulation can also be used to estimate the critical current and DC characteristics of HTS tapes and coils. In [79],

Zhang *et al* used the 2D axisymmetric H -formulation to study the magnetic field distribution of an HTS coil, and determined the coil's critical current by considering the weakest turn of the coil. As a result of the analysis, they suggested a coil (end-to-end) voltage of $20 \mu\text{V/m}$ (instead of the conventional $100 \mu\text{V/m}$) as a new criterion for determining a long term and safe operating current. They also found that the presence of an anti-phase background field changes the position of the weakest turn of the coil. In [69], the 2D axisymmetric H -formulation was used to simulate pancake coils made from a Roebel cable and calculate the critical current density of each HTS layer and the magnitude of the magnetic flux density in and around the coil. In [70], Thakur *et al* studied the voltage-current characteristics and critical currents of superconducting strips and Roebel cables. In [55], Grilli *et al* proved that dynamic simulations using a current ramp and evaluating the average electric field in the superconductor can be a proper method to determine the critical current: their results were in good agreement with a self-consistent DC model and with measurements.

In [80], Ainslie *et al* calculated the DC characteristics and critical current of an HTS coil with magnetic flux diverter under different background magnetic fields. In [81], the DC properties were successfully simulated by a 2D axisymmetric H -formulation model, and the anisotropy and non-uniformity of HTS coils were studied. In [82], Hu *et al* used the measurement of angular dependence of the critical current of HTS tapes, and incorporated the $J_c(B, \theta)$ characteristics into the H -formulation FEM model. Their model could accurately match the critical current and angular dependence of a SuperPower HTS tape (SCS4050), and they found that simulations with the two-variable direct interpolation of the $J_c(B, \theta)$ data were over 100 times faster than those using a data fitting method. In [83], Liu *et al* carried out a comprehensive comparison of critical current simulations of a double pancake racetrack coil with over 200 turns: the H -formulation was used as a comparison for other models, which can be computationally more efficient for this kind of calculation: the T - A formulation (which considers the superconductor layer as an infinitely thin object), and the P -model and modified load-line method (which use static simulations). The predictions of the models were similar to each other and in reasonably good agreement with the experiments.

VI. MAGNETIZATION OF BULKS AND STACKS

In the fundamental studies of HTS modeling, the magnetization pattern of a HTS bulk or strip can be well modelled by H -formulation and the results are in good agreement with analytical solutions [23], [24]. In [84], the magnetization curves of an HTS bulk in the presence of different amplitudes and frequencies of magnetic field were simulated in 2D. In [39], Zhang and Coombs used the 3D H -formulation to model a single HTS bulk and a bulk array, and showed that HTS bulk arrays can create a highly uniform magnetic field profile in a reasonably large domain. In [85], Zhang *et al* examined the pulse magnetization of an HTS bulk and studied

the distribution of trapped field using the H -formulation. In [86], Kapolka *et al* studied different magnetization behaviors of HTS rectangular bulks and stacks in the presence of inclined fields using different 3D models, including the H -formulation.

In [87], Ainslie *et al* performed a pulsed field magnetization (PFM) experiment for two c -axis oriented, single grain GdBCO and YBCO bulk superconductors, and used the 3D H -formulation model to investigate the effects of inhomogeneities on the trapped field and maximum temperature increase of the samples. In [88], a novel arrangement of the HTS bulk with magnetizing coils and iron yoke to trap high field was experimentally tested, and a 2D axisymmetric H -formulation model was used to qualitatively reproduce and monitor the magnetization process from the thermal and electromagnetic points of view. In [89], Ainslie and Fujishiro presented an overview of the modeling of HTS bulk magnetization, and proved that both the 3D and 2D axisymmetric H -formulation models are viable tools for various conditions of HTS bulk research.

In [90], Page *et al* carried out the experiment of pulsed magnetization for HTS stacks using multiple pulses with different temperatures, and used the 2D H -formulation and the real thickness of each layer in the HTS stack to accurately model the process of eddy current and heating effects. In [91], Baskys *et al* simulated trapped magnetic fields and critical current density of HTS stacked tapes with angular transversal field. In [92], [93], Zou *et al* studied the influence of the n index and magnetic field constant B_0 value in the Kim's model on the field trapped in HTS bulks by means of pulsed field magnetization. An example of an HTS bulk coupling cooling boundary and thermal insulation in the presence of pulsed magnetic field is presented in Figure 3, which shows the modeling scheme and the domains and the boundary conditions (Figure 3(a)), the temporal evolution of the applied field pulse (Figure 3(b)) and some results at selected instants of the pulse (Figure 3(c)). In the last plot, the influence of the index n on the results for the current density distribution is clearly visible, as are the different results obtained with a purely electromagnetic model (on the left) and a coupled electromagnetic-thermal model (on the right). In [94], the same authors investigated an HTS stack magnetized using pulsed field magnetization by controlling the current of external coils based on H -formulation. Later, Zou *et al* performed experiments on HTS stack magnetization to validate the electromagnetic-thermal coupled 2D H -formulation model, and the results indicated that using suitable magnetization sequences could efficiently improve the trapped field [95].

VII. LARGE-SCALE HTS APPLICATIONS

The H -formulation can be used to simulate the superconducting parts of large-scale HTS applications, in particular to investigate their electromagnetic performance (e.g. loss analysis) and to study the effect of screening currents.

Shen *et al* used the H -formulation FEM model to develop superconducting magnets using a Halbach array




FIGURE 3. (a) An HTS bulk magnetized by pulsed field magnetization (PFM) with a solenoid using *H*-formulation, the upper boundary of HTS bulk was set as a cooling boundary with a given heat flux, and the other 3 boundaries of the HTS bulk are thermally insulated, (b) The applied magnetic field (normalized to its maximum value), 4 points are selected for analysis: (i) 0.01s, (ii) 0.035s, (iii) 0.06s, (iv) 100s, (c) the normalized current density distributions J/J_c at selected times, with different values of n , with figure source: [92].

configuration for transportable medical imaging device called Lorentz Force Electrical Impedance Tomography (LFEIT) [96], and then they used optimization methods to further improve the uniformity of the superconducting magnet [97]. As shown in Figure 4, Shen *et al* also incorporated the superconducting magnetic properties into the LFEIT system to simulate the magneto-acoustic signal from different biological samples [98]. Xia *et al* evaluated the electromagnetic performance and calculated the AC losses of a high-field superconducting magnet using the *H*-formulation with anisotropic bulk homogenization model, with the purpose of getting insights for the superconducting prototype coils of the National High Magnetic Field Laboratory 32 Tesla all-superconducting magnet [99].

The *H*-formulation can be a useful tool for modeling superconducting fault current limiters. In [100], a 10 kV resistive-type HTS fault current limiter was investigated by means of experiments and *H*-formulation calculations. In [101], Jia *et al* performed a loss and magnetic field analysis of a saturated iron-core superconducting fault current limiter (SISFLC). In addition to the spatial distribution of the AC losses, they studied the relationship between the AC component of the current and the AC losses. In [102], Shen *et al* investigated the details of the power dissipation of a three-phase 35 kV/90 MVA SISFCL. The losses were estimated to be up to the kW level and potentially even higher, depending on the amplitude of the used DC bias current.

Wang *et al* modelled a hybrid HTS magnet with around 7000 turns using the homogeneous bulk approximation. Such magnet was proposed to be applied in a superconducting magnetic energy storage (SMES) system [103]. Using the same homogeneous bulk approximation, Song *et al* simulated




FIGURE 4. (a) Configuration of superconducting Lorentz Force Electrical Impedance Tomography (LFEIT), (b) magneto-acoustic signal from the superconducting LFEIT system, for the tests of two biological samples (output signal with noise), (c) electrical signal imaging of two biological samples, with figure source: [98].

an HTS three-phase 1 MVA transformer, and compared the loss results with those previously obtained with the minimum magnetic energy variation (MMEV) model, finding a reasonably good agreement [104].

Several studies have been reported on the modeling of HTS motor or generator applications based on the *H*-formulation. Hu *et al* used a 3D model to simulate all-superconducting synchronous electric machines, and they performed the analysis on the magnetic field around the HTS coils and proposed a method to reduce the total AC losses [105]. Zhang *et al* simulated the HTS racetrack armature windings for large-scale HTS machines and studied their magnetization and transport current AC losses [106], [107]. For HTS generators, Quéval *et al* combined the power grid analysis and the loss study of a 10 MW class HTS wind turbine generator [108]. Li *et al* modelled the armature structures of a fully HTS synchronous generators with loss and electromagnetic analysis [109]. Brambilla *et al* developed a hybrid *A-H* formulation to investigate the electromagnetic behavior of HTS electrical machines [110]. The idea behind this approach was the separation of the model of an electrical machine in two parts, where the magnetic field is calculated with the most appropriate formulation: the *H*-formulation in the part containing the superconductors and the *A*-formulation in the part containing conventional conductors (and possibly permanent magnets).

The work focused on determining and applying the continuity conditions on the boundary separating the two regions.

VIII. COUPLING WITH THERMAL MODELS

In COMSOL Multiphysics, the H -formulation can be conveniently coupled with other physics modules. A typical thermal model is based on the time-dependent heat transfer equation:

$$C_v \frac{\partial T}{\partial t} = \nabla \cdot (\lambda \nabla T) + Q_{ac} \quad (6)$$

$$Q_{ac} = EJ \quad (7)$$


where T is the temperature, λ and C_v are the thermal conductivity and the volumetric heat capacity. Q_{ac} is the heat dissipation generated by the AC loss which can be calculated using the H -formulation. Roy *et al* used a thermal coupled H -formulation to model the thermal and electromagnetic behavior of HTS tapes for resistive superconducting fault current limiters [111]. Majoros *et al* studied the heat generation and magnetization AC losses in a HTS CORC by measurements and simulations based on the 2D thermal-coupled H -formulation [72]. Song *et al* investigated the AC losses and their impact on the thermal stability of HTS windings in superconducting machines [112]. Huang *et al* presented a numerical study of the YBCO bulk for maglev application together with loss analysis in [113].

Hu *et al* built a thermal-coupled 2D model for HTS tapes using homogenization to analyze the effects of the substrate layer on the lightning current performance of HTS tapes. The simulation results were verified by experiments and proved that the maximum temperature always occurred at the top of the homogenized bulk [114].

Zou *et al* used the electromagnetic-thermal coupled 2D axisymmetric H -formulation bulk models to study the impact of the magnitude and frequency of external AC magnetic fields on the bulk's trapped field profile [115]. As mentioned in section VI, these studies generally incorporated the thermal-coupled model into H -formulation FEM model to achieve more realistic physical characteristics [87]–[89], [94], [95].

IX. COUPLING WITH MECHANICAL MODELS

The mechanical-coupled H -formulation can be used to investigate magnetic forces, levitation and suspension of HTS applications. Ma *et al* developed an analytical model based on the H -formulation solver coupled with force calculation for the magnetic levitation and suspension of HTS applications, and they validated the analytical solutions with experiments [117], [116]. Liu *et al* performed measurements of magnetic levitation with an HTS stacks made of 120 REBCO coated conductor tapes, and showed that the 2D H -formulation model was able to accurately predict the levitation performance [118]. Huang *et al* studied the influence of both intrinsic factors (e.g. critical current density) and external factors (e.g. the moving velocity, and moving path of HTS bulk) on the levitation performance of HTS maglev systems,



(a) Configuration of an experimental HTS flux pump



(b) Equivalent 2D H -formulation FEM model for HTS flux pump

FIGURE 5. (a) Configuration of an experimental HTS flux pump, (b) the equivalent 2D H -formulation FEM model for HTS flux pump.

based on current density distribution and magnetic levitation analysis [119].

Sass *et al* proved that the H -formulation FEM model can be used to calculate the levitation force on HTS stacks and bulks of superconducting bearing applications and that it is a proper approach to model moving objects [120], and the vertical levitation force in y -direction per unit length can be calculated by:

$$F_y(t) = \int_{S_T} [\mu \cdot H_x(x, y, t) \cdot J_z(x, y, t)] dS_T \quad (8)$$

where S_T is the surface of all superconducting regions.

Grilli *et al* used H -formulation and the Arbitrary Lagrangian-Eulerian formulations to model the levitation phenomena of superconducting bulks and permanent magnets with a dynamic mesh approach [121], and Zheng *et al* used a similar method to investigate the electromagnetic characteristics of superconducting maglev devices [122]. Ta and Gao built a 3D electromagnetic-mechanical H -formulation FEM model to study the current density, the magnetic field distribution and the Lorentz force of a Nb_3Sn superconducting strand [123]. Patel *et al* used a force-, field- and temperature-dependent H -formulation model to analyze the induced current density distribution of HTS annuli, made from tapes with ferromagnetic substrate. They found that the presence of the ferromagnetic substrate could enhance the stable axial levitation force to values higher than possible with a uniform bulk of infinite J_c [124].

X. DYNAMIC RESISTANCE AND FLUX PUMPS

The dynamic resistance and flux pumping characteristics of HTS can be modelled with the H -formulation. Ainslie *et al* developed a 2D model to compute the dynamic resistance

and total loss in an HTS coated conductor transporting a DC electric current and in the presence of background AC magnetic fields. This model helped explain the origin and characteristics of dynamic resistance including the relationship with the applied field and current, the onset of nonlinear flux-flow resistance and the threshold field [125]. As shown in Figure 5, Geng *et al* used a 2D H -formulation model to simulate a transformer–rectifier flux pump using the mechanism of switching dynamic resistance. Figure 5(a) shows a typical transformer–rectifier circuit: a superconducting charging loop with varying magnetic field and a superconducting load, and Figure 5(b) shows the corresponding schematic for the FEM modeling using H -formulation. Their analysis showed that the model was capable of simulating the flux pumping behaviors and the simulation results had good agreement with the experimental data [126]. Mataira *et al* used the H -formulation to verify the principle of DC output voltage of an HTS dynamo, and demonstrated the process of large overcritical currents flowing within the HTS stator during certain periods of each dynamo cycle [127].

XI. ADVANTAGES AND DISADVANTAGES

The H -formulation has shown its powerful capability to describe the electromagnetic behavior of a wide range of HTS applications and it is now the standard FEM model used for that purpose. There are several reasons for the popularity of the H -formulation. First and foremost, the H -formulation is easy to implement in the widespread commercial software package COMSOL Multiphysics. This is an important reason, because it opens this kind of simulations to researchers that are not necessarily experts in numerical modeling techniques. Since a few years, the built-in Magnetic Field Formulation (MFH) module in COMSOL Multiphysics makes the use of the H -formulation model even simpler with respect to when equation (3) had to be written in the general Partial Differential Equation (PDE) module. Another advantage of the MFH module with respect to the traditional PDE approach is that it is easier to simulate axisymmetric geometries and consider materials with nonlinear magnetic properties.

In addition, thanks to the widespread use of the H -formulation in COMSOL Multiphysics, it is easier for research groups and the whole community to share FEM models and transfer the knowledge between members of a research group. Some models are publicly available on the website of the HTS Modeling Workgroup [128], which can be useful to learn about problem settings like mesh size, tolerances, etc.

Despite the success, the H -formulation has some important limitations:

(i) For large-scale applications involving HTS coated conductors, the T - A formulation [21], [129], which simulates the superconducting layer as an infinitely thin object, is more efficient than the H -formulation: for example, in [21] the T - A formulation was reported to be about 20 times faster than the H -formulation for the simulation of 500 individual HTS tapes.

(ii) The H -formulation simulates the air domains, and the calculation speed is slower than other methods which do not do that [67].

(iii) This puts also some limits on the number of tapes that can be simulated in 2D, which is typically in the range of several hundred [77]. For larger numbers, the homogenization method is a viable solution, as long as the superconductor layer can be considered infinitely thin (no currents induced across the thickness).

(iv) The possibility of using parallel computing with the H -formulation needs to be better addressed, especially for the solution of large 3D problems [130].

As a final remark, one should also note that, from the mathematical point of view, a more appropriate approach to solve this kind of problems would use scalar potentials in the non-conductive regions and vector fields only in the conductive regions. The advantage of these hybrid formulations should become evident, especially for solving 3D problems of increasing complexity. Some initial steps in that direction have recently been taken [131].

XII. CONCLUSION

This article presented a systematic review on the simulation of high temperature superconductors and their applications using the H -formulation FEM model. This model has been and still is primarily used for calculating AC losses, but it can also be used for other purposes, like simulation of DC characteristics and calculation of trapped fields and flux pumps. The simulation of multi-physics problems, particularly electromagnetic-thermal and electromagnetic-mechanical coupled problems, is facilitated by the implementation in the COMSOL Multiphysics finite-element program. The H -formulation has been also implemented in other programming environments, but they represent a minority.

Numerous studies demonstrated that the H -formulation FEM model is one of the most reliable numerical modeling methods to simulate various HTS applications – from simple topologies like HTS bulks, tapes, coils, to devices and large-scale applications – with good agreement with experiments and a reasonable computation speed. This paper reviewed the previous HTS studies based on H -formulation FEM models, starting from the basics of the formulation, and following its evolution towards cases of increasing complexity, both from the geometrical and physical point of view. Although the recently developed T - A formulation is becoming popular for the simulation of HTS coated conductors, the H -formulation is much more flexible and, for the foreseeable future, it is expected to retain a major role for the simulation of superconducting applications.

REFERENCES

- [1] D. Larbalestier, A. Gurevich, D. M. Feldmann, and A. Polyanskii, “High- T_c superconducting materials for electric power applications,” *Nature*, vol. 414, no. 6861, pp. 368–377, Nov. 2001.
- [2] O. Tsukamoto, “Ways for power applications of high temperature superconductors to go into the real world,” *Supercond. Sci. Technol.*, vol. 17, no. 5, pp. 185–190, Mar. 2004.

- [3] S. Hahn, K. Kim, K. Kim, X. Hu, T. Painter, I. Dixon, S. Kim, K. R. Bhattacharai, S. Noguchi, J. Jaroszynski, and D. C. Larbalestier, "45.5-tesla direct-current magnetic field generated with a high-temperature superconducting magnet," *Nature*, vol. 570, no. 7762, pp. 496–499, Jun. 2019.
- [4] H. W. Weijers, H. Kandel, H. Bai, A. V. Gavrilin, Y. L. Viouchkov, D. C. Larbalestier, D. V. Abramov, W. D. Markiewicz, A. J. Voran, S. R. Gundlach, W. R. Sheppard, B. Jarvis, Z. L. Johnson, P. D. Noyes, and J. Lu, "Progress in the development of a superconducting 32 t magnet with REBCO high field coils," *IEEE Trans. Appl. Supercond.*, vol. 24, no. 3, Jun. 2014, Art. no. 4301805.
- [5] H. W. Weijers, U. P. Trociewitz, W. D. Markiewicz, J. Jiang, D. Myers, E. E. Hellstrom, A. Xu, J. Jaroszynski, P. Noyes, Y. Viouchkov, and D. C. Larbalestier, "High field magnets with HTS conductors," *IEEE Trans. Appl. Supercond.*, vol. 20, no. 3, pp. 576–582, Jun. 2010.
- [6] M. Noe and M. Steurer, "High-temperature superconductor fault current limiters: Concepts, applications, and development status," *Supercond. Sci. Technol.*, vol. 20, no. 3, pp. 15–29, Jan. 2007.
- [7] M. Chen, W. Paul, M. Lakner, L. Donzel, M. Hoidis, P. Unteraehrer, R. Weder, and M. Mendik, "6.4 MVA resistive fault current limiter based on bi-2212 superconductor," *Phys. C, Supercond.*, vols. 372–376, pp. 1657–1663, Aug. 2002.
- [8] L. Ye and A. M. Campbell, "Case study of HTS resistive superconducting fault current limiter in electrical distribution systems," *Electr. Power Syst. Res.*, vol. 77, nos. 5–6, pp. 534–539, Apr. 2007.
- [9] Y. Xin, W. Gong, X. Niu, Z. Cao, J. Zhang, B. Tian, H. Xi, Y. Wang, H. Hong, Y. Zhang, B. Hou, and X. Yang, "Development of saturated iron core HTS fault current limiters," *IEEE Trans. Appl. Supercond.*, vol. 17, no. 2, pp. 1760–1763, Jun. 2007.
- [10] Z. Huang, H. S. Ruiz, Y. Zhai, J. Geng, B. Shen, and T. A. Coombs, "Study of the pulsed field magnetization strategy for the superconducting rotor," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 4, Jun. 2016, Art. no. 5202105.
- [11] B. Gamble, G. Snitchler, and T. MacDonald, "Full power test of a 36.5 MW HTS propulsion motor," *IEEE Trans. Appl. Supercond.*, vol. 21, no. 3, pp. 1083–1088, Jun. 2011.
- [12] G. Snitchler, B. Gamble, C. King, and P. Winn, "10 MW class superconductor wind turbine generators," *IEEE Trans. Appl. Supercond.*, vol. 21, no. 3, pp. 1089–1092, Jun. 2011.
- [13] P. J. Masson, G. V. Brown, D. S. Soban, and C. A. Luongo, "HTS machines as enabling technology for all-electric airborne vehicles," *Supercond. Sci. Technol.*, vol. 20, no. 8, pp. 748–756, Aug. 2007.
- [14] J. Geng, K. Matsuda, L. Fu, B. Shen, X. Zhang, and T. A. Coombs, "Operational research on a high- T_c rectifier-type superconducting flux pump," *Supercond. Sci. Technol.*, vol. 29, no. 3, Mar. 2016, Art. no. 035015.
- [15] J. Geng, K. Matsuda, L. Fu, J.-F. Fagnard, H. Zhang, X. Zhang, B. Shen, Q. Dong, M. Baghdadi, and T. A. Coombs, "Origin of DC voltage in type II superconducting flux pumps: Field, field rate of change, and current density dependence of resistivity," *J. Phys. D, Appl. Phys.*, vol. 49, no. 11, Mar. 2016, Art. no. 11LT01.
- [16] N. D. Glasson, M. P. Staines, Z. Jiang, and N. S. Allpress, "Verification testing for a 1 MVA 3-Phase demonstration transformer using 2G-HTS roebel cable," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 5500206.
- [17] M. Staines, N. Glasson, M. Pannu, K. P. Thakur, R. Badcock, N. Allpress, P. D'Souza, and E. Talantsev, "The development of a roebel cable based 1 MVA HTS transformer," *Supercond. Sci. Technol.*, vol. 25, no. 1, Jan. 2012, Art. no. 014002.
- [18] Y. Wang, X. Zhao, J. Han, H. Li, Y. Guan, Q. Bao, L. Xiao, L. Lin, X. Xu, N. Song, and F. Zhang, "Development of a 630 kVA three-phase HTS transformer with amorphous alloy cores," *IEEE Trans. Appl. Supercond.*, vol. 17, no. 2, pp. 2051–2054, Jun. 2007.
- [19] D. Ruiz-Alonso, T. Coombs, and A. Campbell, "Computer modelling of high-temperature superconductors using an A–V formulation," *Supercond. Sci. Technol.*, vol. 17, no. 5, pp. 305–310, Apr. 2004.
- [20] N. Amemiya, S.-I. Murasawa, N. Banno, and K. Miyamoto, "Numerical modelings of superconducting wires for AC loss calculations," *Phys. C, Supercond.*, vol. 310, nos. 1–4, pp. 16–29, Dec. 1998.
- [21] H. Zhang, M. Zhang, and W. Yuan, "An efficient 3D finite element method model based on the T-A formulation for superconducting coated conductors," *Supercond. Sci. Technol.*, vol. 30, no. 2, Feb. 2017, Art. no. 024005.
- [22] R. Pecher, "3D-modelling of bulk type II superconductors using unconstrained H-formulation," in *Proc. 6th EUCAS*, Sorrento, Italy, 2003.
- [23] Z. Hong, A. M. Campbell, and T. A. Coombs, "Numerical solution of critical state in superconductivity by finite element software," *Supercond. Sci. Technol.*, vol. 19, no. 12, pp. 1246–1252, Dec. 2006.
- [24] R. Brambilla, F. Grilli, and L. Martini, "Development of an edge-element model for AC loss computation of high-temperature superconductors," *Supercond. Sci. Technol.*, vol. 20, no. 1, pp. 16–24, Jan. 2007.
- [25] K. Kajikawa, T. Hayashi, R. Yoshida, M. Iwakuma, and K. Funaki, "Numerical evaluation of AC losses in HTS wires with 2D FEM formulated by self magnetic field," *IEEE Trans. Applied Supercond.*, vol. 13, no. 2, pp. 3630–3633, Jun. 2003.
- [26] C. P. Bean, "Magnetization of hard superconductors," *Phys. Rev. Lett.*, vol. 8, no. 6, pp. 250–253, Mar. 1962.
- [27] F. Sirois, F. Grilli, and A. Morandi, "Comparison of constitutive laws for modelling high-temperature superconductors," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 1, Jan. 2019, Art. no. 8000110.
- [28] Y. Li, N. Tominaga, Y. Sogabe, T. Kikuchi, S. Wimbush, S. Granville, and N. Amemiya, "Influence of E–J characteristics of coated conductors and field ramp-up rates on shielding-current-induced fields of magnet," *IEEE Trans. Appl. Supercond.*, vol. 28, no. 3, Apr. 2018, Art. no. 4601105.
- [29] V. M. R. Zermeno, F. Grilli, and F. Sirois, "A full 3D time-dependent electromagnetic model for roebel cables," *Supercond. Sci. Technol.*, vol. 26, no. 5, May 2013, Art. no. 052001.
- [30] V. Lahtinen, M. Lyly, A. Stenvall, and T. Tarhasaari, "Comparison of three eddy current formulations for superconductor hysteresis loss modelling," *Supercond. Sci. Technol.*, vol. 25, no. 11, Nov. 2012, Art. no. 115001.
- [31] C. Lorin and P. J. Masson, "Numerical analysis of the impact of elliptical fields on magnetization losses," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 8201405.
- [32] G. Escamez, F. Sirois, V. Lahtinen, A. Stenvall, A. Badel, P. Tixador, B. Ramdane, G. Meunier, R. Perrin-Bit, and C.-E. Bruzek, "3-D numerical modeling of AC losses in multifilamentary MgB₂ wires," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 3, 2016, Art. no. 4701907.
- [33] *Superconductors*. Accessed: Mar. 16, 2020. [Online]. Available: <https://gitlab.onelab.info/doc/models/wikis/Superconductors>
- [34] F. Grilli, R. Brambilla, and L. Martini, "Modeling high-temperature superconducting tapes by means of edge finite elements," *IEEE Trans. Appl. Supercond.*, vol. 17, no. 2, pp. 3155–3158, Jun. 2007.
- [35] F. Grilli and S. P. Ashworth, "Measuring transport AC losses in YBCO-coated conductor coils," *Supercond. Sci. Technol.*, vol. 20, no. 8, pp. 794–799, Aug. 2007.
- [36] Z. Hong and T. A. Coombs, "Numerical modelling of AC loss in coated conductors by finite element software using h formulation," *J. Supercond. Novel Magn.*, vol. 23, no. 8, pp. 1551–1562, Dec. 2010.
- [37] V. M. R. Zermeno, A. B. Abrahamsen, N. Mijatovic, B. B. Jensen, and M. P. Sørensen, "Calculation of alternating current losses in stacks and coils made of second generation high temperature superconducting tapes for large scale applications," *J. Appl. Phys.*, vol. 114, no. 17, Nov. 2013, Art. no. 173901.
- [38] V. M. Rodriguez-Zermeno, N. Mijatovic, C. Traeholt, T. Zirngibl, E. Seiler, A. B. Abrahamsen, N. F. Pedersen, and M. P. Sørensen, "Towards faster FEM simulation of thin film superconductors: A multiscale approach," *IEEE Trans. Appl. Supercond.*, vol. 21, no. 3, pp. 3273–3276, Jun. 2011.
- [39] M. Zhang and T. Coombs, "3D modeling of high- T_c superconductors by finite element software," *Supercond. Sci. Technol.*, vol. 25, no. 1, Dec. 2011, Art. no. 015009.
- [40] F. Grilli, R. Brambilla, F. Sirois, A. Stenvall, and S. Memiaghe, "Development of a three-dimensional finite-element model for high-temperature superconductors based on the H-formulation," *Cryogenics*, vol. 53, pp. 142–147, Jan. 2013.
- [41] V. M. R. Zermeno and F. Grilli, "3D modeling and simulation of 2G HTS stacks and coils," *Supercond. Sci. Technol.*, vol. 27, no. 4, Apr. 2014, Art. no. 044025.
- [42] M. Zhang, J. Kvitkovic, S. V. Pamidi, and T. A. Coombs, "Experimental and numerical study of a YBCO pancake coil with a magnetic substrate," *Supercond. Sci. Technol.*, vol. 25, no. 12, Dec. 2012, Art. no. 125020.
- [43] B. Shen, C. Li, J. Geng, Q. Dong, J. Ma, J. Gawith, K. Zhang, Z. Li, J. Chen, W. Zhou, X. Li, J. Sheng, Z. Li, Z. Huang, J. Yang, and T. A. Coombs, "Power dissipation in the HTS coated conductor tapes and coils under the action of different oscillating currents and fields," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 5, Aug. 2019, Art. no. 8201105.

- [44] F. Liang, W. Yuan, M. Zhang, Z. Zhang, J. Li, S. Venuturumilli, and J. Patel, "AC loss modelling and experiment of two types of low-inductance solenoidal coils," *Supercond. Sci. Technol.*, vol. 29, no. 11, Nov. 2016, Art. no. 115006.
- [45] H. Daffix and P. Tixador, "Electrical AC loss measurements in superconducting coils," *IEEE Trans. Applied Supercond.*, vol. 7, no. 2, pp. 286–289, Jun. 1997.
- [46] M. Oomen, "AC loss in superconducting tapes and cables," Ph.D. dissertation, Dept. Low Temp. Division, Univ. Twente, Enschede, The Netherlands, 2000.
- [47] W. T. Norris, "Calculation of hysteresis losses in hard superconductors carrying AC: Isolated conductors and edges of thin sheets," *J. Phys. D, Appl. Phys.*, vol. 3, no. 4, pp. 489–507, Apr. 1970.
- [48] E. H. Brandt and M. Indenbom, "Type-II-superconductor strip with current in a perpendicular magnetic field," *Phys. Rev. B, Condens. Matter*, vol. 48, no. 17, pp. 893–906, 1993.
- [49] G. P. Mikitik, Y. Mawatari, A. T. S. Wan, and F. Sirois, "Analytical methods and formulas for modeling high temperature superconductors," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 2, Apr. 2013, Art. no. 8001920.
- [50] F. Grilli, E. Pardo, A. Stenvall, D. N. Nguyen, W. Yuan, and F. Gomory, "Computation of losses in HTS under the action of varying magnetic fields and currents," *IEEE Trans. Appl. Supercond.*, vol. 24, no. 1, pp. 78–110, Feb. 2014.
- [51] B. Shen, J. Li, J. Geng, L. Fu, X. Zhang, H. Zhang, C. Li, F. Grilli, and T. A. Coombs, "Investigation of AC losses in horizontally parallel HTS tapes," *Supercond. Sci. Technol.*, vol. 30, no. 7, Jul. 2017, Art. no. 075006.
- [52] B. Shen, J. Geng, X. Zhang, L. Fu, C. Li, H. Zhang, Q. Dong, J. Ma, J. Gawith, and T. A. Coombs, "AC losses in horizontally parallel HTS tapes for possible wireless power transfer applications," *Phys. C, Supercond. Appl.*, vol. 543, pp. 35–40, Dec. 2017.
- [53] B. Shen, T. Coombs, and F. Grilli, "AC loss analysis on HTS Cross-Conductor (CroCo) cables for power transmission," in *Proc. IEEE Int. Conf. Appl. Supercond. Electromagn. Devices (ASEMD)*, Apr. 2018, pp. 1–2.
- [54] E. Pardo and F. Grilli, "Numerical simulations of the angular dependence of magnetization AC losses: Coated conductors, roebel cables and double pancake coils," *Supercond. Sci. Technol.*, vol. 25, no. 1, Jan. 2012, Art. no. 014008.
- [55] F. Grilli, F. Sirois, V. M. R. Zermeno, and M. Vojenciak, "Self-consistent modeling of the I_c of HTS devices: How accurate do models really need to be?" *IEEE Trans. Appl. Supercond.*, vol. 24, no. 6, Dec. 2014, Art. no. 8000508.
- [56] B. Shen, C. Li, J. Geng, X. Zhang, J. Gawith, J. Ma, Y. Liu, F. Grilli, and T. A. Coombs, "Power dissipation in HTS coated conductor coils under the simultaneous action of AC and DC currents and fields," *Supercond. Sci. Technol.*, vol. 31, no. 7, Jul. 2018, Art. no. 075005.
- [57] D. N. Nguyen, S. P. Ashworth, J. O. Willis, F. Sirois, and F. Grilli, "A new finite-element method simulation model for computing AC loss in roll assisted biaxially textured substrate YBCO tapes," *Supercond. Sci. Technol.*, vol. 23, no. 2, Feb. 2010, Art. no. 025001.
- [58] B. Shen, J. Li, J. Geng, L. Fu, X. Zhang, C. Li, H. Zhang, Q. Dong, J. Ma, and T. A. Coombs, "Investigation and comparison of AC losses on stabilizer-free and copper stabilizer HTS tapes," *Phys. C, Supercond. Appl.*, vol. 541, pp. 40–44, Oct. 2017.
- [59] Z. Hong, W. Yuan, M. Ainslie, Y. Yan, R. Pei, and T. A. Coombs, "AC losses of superconducting racetrack coil in various magnetic conditions," *IEEE Trans. Appl. Supercond.*, vol. 21, no. 3, pp. 2466–2469, Jun. 2011.
- [60] Z. Xu and F. Grilli, "Modelling AC ripple currents in HTS coated conductors," *Supercond. Sci. Technol.*, vol. 28, no. 10, Oct. 2015, Art. no. 104002.
- [61] V. Lahtinen, E. Pardo, J. Šouc, M. Solovyov, and A. Stenvall, "Ripple field losses in direct current biased superconductors: Simulations and comparison with measurements," *J. Appl. Phys.*, vol. 115, no. 11, Mar. 2014, Art. no. 113907.
- [62] V. Lahtinen and A. Stenvall, "The difficulty of modeling ripple field losses in superconductors using the eddy current model," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 4900505.
- [63] D. N. Nguyen, F. Grilli, S. P. Ashworth, and J. O. Willis, "AC loss study of antiparallel connected YBCO coated conductors," *Supercond. Sci. Technol.*, vol. 22, no. 5, May 2009, Art. no. 055014.
- [64] E. Demencik, M. Vojenciak, A. Kario, R. Nast, A. Jung, W. Goldacker, and F. Grilli, "AC loss and coupling currents in YBCO coated conductors with varying number of filaments," *IEEE Trans. Appl. Supercond.*, vol. 24, no. 6, pp. 1–8, Dec. 2014.
- [65] F. Grilli, V. M. R. Zermeno, and M. Takayasu, "Numerical modeling of twisted stacked tape cables for magnet applications," *Phys. C, Supercond. Appl.*, vol. 518, pp. 122–125, Nov. 2015.
- [66] V. Zermeno, P. Krüger, M. Takayasu, and F. Grilli, "Modeling and simulation of termination resistances in superconducting cables," *Supercond. Sci. Technol.*, vol. 27, no. 12, Dec. 2014, Art. no. 124013.
- [67] F. Grilli and E. Pardo, "Simulation of AC loss in roebel coated conductor cables," *Supercond. Sci. Technol.*, vol. 23, no. 11, Nov. 2010, Art. no. 115018.
- [68] F. Grilli, V. Zermeno, M. Vojenciak, E. Pardo, A. Kario, and W. Goldacker, "AC losses of pancake coils made of roebel cable," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 5900205.
- [69] F. Grilli, V. M. R. Zermeno, E. Pardo, M. Vojenciak, J. Brand, A. Kario, and W. Goldacker, "Self-field effects and AC losses in pancake coils assembled from coated conductor roebel cables," *IEEE Trans. Appl. Supercond.*, vol. 24, no. 3, Jun. 2014, Art. no. 4801005.
- [70] K. P. Thakur, A. Raj, E. H. Brandt, J. Kvitkovic, and S. V. Pamidi, "Frequency-dependent critical current and AC loss of superconductor strip and roebel cable," *Supercond. Sci. Technol.*, vol. 24, no. 6, Jun. 2011, Art. no. 065024.
- [71] F. Grilli, M. Vojenciak, A. Kario, and V. Zermeno, "HTS roebel cables: Self-field critical current and AC losses under simultaneous application of transport current and magnetic field," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 4, Jun. 2016, Art. no. 4803005.
- [72] M. Majoros, M. D. Sumption, E. W. Collings, and D. C. van der Laan, "Magnetization losses in superconducting YBCO conductor-on-round-core (CORC) cables," *Supercond. Sci. Technol.*, vol. 27, no. 12, Dec. 2014, Art. no. 125008.
- [73] R. Terzioğlu, M. Vojenciak, J. Sheng, F. Gömöry, T. F. Çavu, and I. Belenli, "AC loss characteristics of CORC cable with a cu former," *Supercond. Sci. Technol.*, vol. 30, no. 8, Aug. 2017, Art. no. 085012.
- [74] M. Wang, Z. Li, Y. Zhang, C. Sun, F. Dong, Y. Pan, L. Yao, Z. Hong, and Z. Jin, "Three-dimensional numerical study on transport AC loss of soldered-stacked-square-twisted (3S-T) wire," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 2, Mar. 2019, Art. no. 5900105.
- [75] C. Kan, Y. Wang, X. Yuan, Y. Li, and Y. Hou, "AC loss analysis on a quasi-isotropic strand stacked by 2G wires by numerical simulation in cryogenic temperature," *IEEE Trans. Appl. Supercond.*, vol. 28, no. 3, Apr. 2018, Art. no. 8200206.
- [76] B. Shen, T. Coombs, and F. Grilli, "Investigation of AC loss in HTS cross-conductor cables for electrical power transmission," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 2, Mar. 2019, Art. no. 5900205.
- [77] L. Quéval, V. M. R. Zermeno, and F. Grilli, "Numerical models for AC loss calculation in large-scale applications of HTS coated conductors," *Supercond. Sci. Technol.*, vol. 29, no. 2, Feb. 2016, Art. no. 024007.
- [78] B. Shen, F. Grilli, and T. Coombs, "Review of the AC loss computation for HTS using h formulation," *Supercond. Sci. Technol.*, vol. 33, no. 3, Mar. 2020, Art. no. 033002.
- [79] M. Zhang, J.-H. Kim, S. Pamidi, M. Chudy, W. Yuan, and T. A. Coombs, "Study of second generation, high-temperature superconducting coils: Determination of critical current," *J. Appl. Phys.*, vol. 111, no. 8, Apr. 2012, Art. no. 083902.
- [80] M. D. Ainslie, D. Hu, J. Zou, and D. A. Cardwell, "Simulating the in-field AC and DC performance of high-temperature superconducting coils," *IEEE Trans. Appl. Supercond.*, vol. 25, no. 3, Jun. 2015, Art. no. 4602305.
- [81] D. Hu, M. D. Ainslie, J. Zou, and D. A. Cardwell, "Numerical analysis of non-uniformities and anisotropy in high-temperature superconducting coils," *IEEE Trans. Appl. Supercond.*, vol. 25, no. 3, Jun. 2015, Art. no. 4900605.
- [82] D. Hu, M. D. Ainslie, M. J. Raine, D. P. Hampshire, and J. Zou, "Modeling and comparison of in-field critical current density anisotropy in high-temperature superconducting (HTS) coated conductors," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 3, Apr. 2016, Art. no. 6600906.
- [83] Y. Liu, J. Ou, F. Grilli, F. Schreiner, V. M. R. Zermeno, M. Zhang, and M. Noe, "Comparison of 2D simulation models to estimate the critical current of a coated superconducting coil," *Supercond. Sci. Technol.*, vol. 32, no. 1, Jan. 2019, Art. no. 014001.
- [84] Z. Hong, A. M. Campbell, and T. A. Coombs, "Computer modeling of magnetisation in high temperature bulk superconductors," *IEEE Trans. Appl. Supercond.*, vol. 17, no. 2, pp. 3761–3764, Jun. 2007.

- [85] M. Zhang, K. Matsuda, and T. A. Coombs, "New application of temperature-dependent modelling of high temperature superconductors: Quench propagation and pulse magnetization," *J. Appl. Phys.*, vol. 112, no. 4, Aug. 2012, Art. no. 043912.
- [86] M. Kapolka, V. Zermeno, S. Zou, A. Morandi, P. Ribani, E. Pardo, and F. Grilli, "Three-dimensional modeling of the magnetization of superconducting rectangular-based bulks and tape stacks," *IEEE Trans. Appl. Supercond.*, vol. 28, no. 4, 2018, Art. no. 8201206.
- [87] M. D. Ainslie, H. Fujishiro, T. Ujiie, J. Zou, A. R. Dennis, Y.-H. Shi, and D. A. Cardwell, "Modelling and comparison of trapped fields in (RE)BCO bulk superconductors for activation using pulsed field magnetization," *Supercond. Sci. Technol.*, vol. 27, no. 6, Jun. 2014, Art. no. 065008.
- [88] M. D. Ainslie, H. Fujishiro, H. Mochizuki, K. Takahashi, Y.-H. Shi, D. K. Namburi, J. Zou, D. Zhou, A. R. Dennis, and D. A. Cardwell, "Enhanced trapped field performance of bulk high-temperature superconductors using split coil, pulsed field magnetization with an iron yoke," *Supercond. Sci. Technol.*, vol. 29, no. 7, Jul. 2016, Art. no. 074003.
- [89] M. D. Ainslie and H. Fujishiro, "Modelling of bulk superconductor magnetization," *Supercond. Sci. Technol.*, vol. 28, no. 5, May 2015, Art. no. 053002.
- [90] A. G. Page, A. Patel, A. Baskys, S. C. Hopkins, V. Kalitka, A. Molodyk, and B. A. Glowacki, "The effect of stabilizer on the trapped field of stacks of superconducting tape magnetized by a pulsed field," *Supercond. Sci. Technol.*, vol. 28, no. 8, Aug. 2015, Art. no. 085009.
- [91] A. Baskys, A. Patel, S. Hopkins, and B. Glowacki, "Modeling of trapped fields by stacked (RE)BCO tape using angular transversal field dependency," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 3, Feb. 2016, Art. no. 6601004.
- [92] S. Zou, *Magnetization of High Temperature Superconducting Trapped-Field Magnets*. Karlsruhe, Germany: KIT Scientific, 2017.
- [93] S. Zou, V. M. R. Zermeno, and F. Grilli, "Influence of parameters on the simulation of HTS bulks magnetized by pulsed field magnetization," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 4, Jun. 2016, Art. no. 4702405.
- [94] S. Zou, V. M. R. Zermeno, and F. Grilli, "Simulation of stacks of high-temperature superconducting coated conductors magnetized by pulsed field magnetization using controlled magnetic density distribution coils," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 3, Apr. 2016, Art. no. 8200705.
- [95] S. Zou, V. M. R. Zermeno, A. Baskys, A. Patel, F. Grilli, and B. A. Glowacki, "Simulation and experiments of stacks of high temperature superconducting coated conductors magnetized by pulsed field magnetization with multi-pulse technique," *Supercond. Sci. Technol.*, vol. 30, no. 1, Jan. 2017, Art. no. 014010.
- [96] B. Shen, L. Fu, J. Geng, H. Zhang, X. Zhang, Z. Zhong, Z. Huang, and T. Coombs, "Design of a superconducting magnet for lorentz force electrical impedance tomography (LFET)," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 3, Dec. 2016, Art. no. 4400205.
- [97] B. Shen, J. Geng, C. Li, X. Zhang, L. Fu, H. Zhang, J. Ma, and T. A. Coombs, "Optimization study on the magnetic field of superconducting Halbach array magnet," *Phys. C, Supercond. Appl.*, vol. 538, pp. 46–51, Jul. 2017.
- [98] B. Shen, L. Fu, J. Geng, X. Zhang, H. Zhang, Q. Dong, C. Li, J. Li, and T. Coombs, "Design and simulation of superconducting lorentz force electrical impedance tomography (LFEIT)," *Phys. C, Supercond.*, vol. 524, pp. 5–12, May 2016.
- [99] J. Xia, H. Bai, J. Lu, A. V. Gavrillin, Y. Zhou, and H. W. Weijers, "Electromagnetic modeling of REBCO high field coils by the H-formulation," *Supercond. Sci. Technol.*, vol. 28, no. 12, Dec. 2015, Art. no. 125004.
- [100] Z. Hong, J. Sheng, J. Zhang, B. Lin, L. Ying, Y. Li, and Z. Jin, "The development and performance test of a 10 kV resistive type superconducting fault current limiter," *IEEE Trans. Appl. Supercond.*, vol. 22, no. 3, Jun. 2012, Art. no. 5600504.
- [101] Y. Jia, M. D. Ainslie, D. Hu, and J. Yuan, "Numerical simulation and analysis of a saturated-core-type superconducting fault current limiter," *IEEE Trans. Appl. Supercond.*, vol. 27, no. 4, Jun. 2017, Art. no. 5600805.
- [102] B. Shen, C. Li, J. Geng, Q. Dong, J. Ma, J. Gawith, K. Zhang, J. Yang, X. Li, Z. Huang, and T. A. Coombs, "Investigation on power dissipation in the saturated iron-core superconducting fault current limiter," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 2, Mar. 2019, Art. no. 5600305.
- [103] Z. Wang, Y. Tang, L. Ren, J. Li, Y. Xu, Y. Liao, and X. Deng, "AC loss analysis of a hybrid HTS magnet for SMES based on H-Formulation," *IEEE Trans. Appl. Supercond.*, vol. 27, no. 4, Jun. 2017, Art. no. 4701005.
- [104] W. Song, Z. Jiang, X. Zhang, M. Staines, R. A. Badcock, J. Fang, Y. Sogabe, and N. Amemiya, "AC loss simulation in a HTS 3-Phase 1 MVA transformer using h formulation," *Cryogenics*, vol. 94, pp. 14–21, Sep. 2018.
- [105] D. Hu, M. D. Ainslie, J. Zou, and D. A. Cardwell, "3D modelling of all-superconducting synchronous electric machines by the finite element method," in *Proc. COMSOL Conf.*, Cambridge, U.K., 2014, pp. 1–7.
- [106] M. Zhang, M. Chudy, W. Wang, Y. Chen, Z. Huang, Z. Zhong, W. Yuan, J. Kvitkovic, S. V. Pamidi, and T. A. Coombs, "AC loss estimation of HTS armature windings for electric machines," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 5900604.
- [107] M. Zhang, W. Yuan, J. Kvitkovic, and S. Pamidi, "Total AC loss study of 2G HTS coils for fully HTS machine applications," *Supercond. Sci. Technol.*, vol. 28, no. 11, Nov. 2015, Art. no. 115011.
- [108] L. Queval and H. Ohsaki, "AC losses of a grid-connected superconducting wind turbine generator," *IEEE Trans. Appl. Supercond.*, vol. 23, no. 3, Jun. 2013, Art. no. 5201905.
- [109] Y. Li, F. Feng, Y. Li, P. Song, S. Zou, M. Wu, C. Gu, P. Zeng, and T. Qu, "Numerical study on AC loss characteristics of REBCO armature windings in a 15-kW class fully HTS generator," *IEEE Trans. Appl. Supercond.*, vol. 27, no. 4, Jun. 2017, Art. no. 5200206.
- [110] R. Brambilla, F. Grilli, L. Martini, M. Bocchi, and G. Angeli, "A finite-element method framework for modeling rotating machines with superconducting windings," *IEEE Trans. Appl. Supercond.*, vol. 28, no. 5, Aug. 2018, Art. no. 5207511.
- [111] F. Roy, B. Dutoit, F. Grilli, and F. Sirois, "Magneto-thermal modeling of second-generation HTS for resistive fault current limiter design purposes," *IEEE Trans. Appl. Supercond.*, vol. 18, no. 1, pp. 29–35, Mar. 2008.
- [112] X. Song, N. Mijatovic, S. Zou, B. B. Jensen, and J. Holboll, "AC losses and their thermal effect in high-temperature superconducting machines," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 4, Jun. 2016, Art. no. 5900105.
- [113] Z. Huang, Z. Deng, L. Jin, Y. Hong, J. Zheng, and E. F. Rodriguez, "Numerical simulation and experimental analysis on the AC losses of HTS bulks levitating under a varying external magnetic field," *IEEE Trans. Appl. Supercond.*, vol. 29, no. 5, Aug. 2019, Art. no. 8201505.
- [114] D. Hu, J. W. Zhang, A. F. Zhao, Y. W. He, D. M. Xi, H. Huang, B. G. Wei, Z. Y. Li, Z. Hong, and Z. Jin, "Influence of the substrate layer on the lightning current performance of YBa₂Cu₃O_{7- δ} tapes," *J. Supercond. Novel Magn.*, vol. 30, no. 10, pp. 2717–2725, Oct. 2017.
- [115] J. Zou, M. D. Ainslie, D. Hu, and D. A. Cardwell, "Influence of time-varying external magnetic fields on trapped fields in bulk superconductors," *IEEE Trans. Appl. Supercond.*, vol. 25, no. 3, Jun. 2015, Art. no. 4900505.
- [116] G.-T. Ma, J.-S. Wang, and S.-Y. Wang, "3-D modeling of high- T_c superconductor for magnetic levitation/suspension application—Part I: Introduction to the method," *IEEE Trans. Appl. Supercond.*, vol. 20, no. 4, pp. 2219–2227, Aug. 2010.
- [117] G.-T. Ma, J.-S. Wang, and S.-Y. Wang, "3-D modeling of high- T_c superconductor for magnetic levitation/suspension application—Part II: Validation with experiment," *IEEE Trans. Appl. Supercond.*, vol. 20, no. 4, pp. 2228–2234, Aug. 2010.
- [118] K. Liu, W. Yang, G. Ma, L. Quéval, T. Gong, C. Ye, X. Li, and Z. Luo, "Experiment and simulation of superconducting magnetic levitation with REBCO coated conductor stacks," *Supercond. Sci. Technol.*, vol. 31, no. 1, Jan. 2018, Art. no. 015013.
- [119] H. Huang, J. Zheng, H. Liao, Y. Hong, H. Li, and Z. Deng, "Effect laws of different factors on levitation characteristics of high- t_c superconducting maglev system with numerical solutions," *J. Supercond. Novel Magn.*, vol. 32, no. 8, pp. 2351–2358, Aug. 2019.
- [120] F. Sass, G. G. Sotelo, R. D. A. Junior, and F. Sirois, "H-formulation for simulating levitation forces acting on HTS bulks and stacks of 2G coated conductors," *Supercond. Sci. Technol.*, vol. 28, no. 12, Dec. 2015, Art. no. 125012.
- [121] F. Grilli, A. Morandi, F. D. Silvestri, and R. Brambilla, "Dynamic modeling of levitation of a superconducting bulk by coupled H-magnetic field and arbitrary Lagrangian–Eulerian formulations," *Supercond. Sci. Technol.*, vol. 31, no. 12, Dec. 2018, Art. no. 125003.
- [122] J. Zheng, H. Huang, S. Zhang, and Z. Deng, "A general method to simulate the electromagnetic characteristics of HTS maglev systems by finite element software," *IEEE Trans. Appl. Supercond.*, vol. 28, no. 5, Feb. 2018, Art. no. 3600808.

- [123] W. Ta and Y. Gao, "Electromagnetic-mechanical coupling analysis of Nb 3 Sn superconducting strand," *IEEE Trans. Appl. Supercond.*, vol. 26, no. 4, Jun. 2016, Art. no. 6001205.
- [124] A. Patel, S. Hahn, J. Voccio, A. Baskys, S. C. Hopkins, and B. A. Glowacki, "Magnetic levitation using a stack of high temperature superconducting tape annuli," *Supercond. Sci. Technol.*, vol. 30, no. 2, Feb. 2017, Art. no. 024007.
- [125] M. D. Ainslie, C. W. Bumby, Z. Jiang, R. Toyomoto, and N. Amemiya, "Numerical modelling of dynamic resistance in high-temperature superconducting coated-conductor wires," *Supercond. Sci. Technol.*, vol. 31, no. 7, 2018, Art. no. 074003.
- [126] J. Geng and T. A. Coombs, "Modeling methodology for a HTS flux pump using a 2D H-formulation," *Supercond. Sci. Technol.*, vol. 31, no. 12, Dec. 2018, Art. no. 125015.
- [127] R. C. Mataira, M. D. Ainslie, R. A. Badcock, and C. W. Bumby, "Origin of the DC output voltage from a high-*t_c* superconducting dynamo," *Appl. Phys. Lett.*, vol. 114, no. 16, Apr. 2019, Art. no. 162601.
- [128] *HTS Modelling*. Accessed: Mar. 18, 2020. [Online]. Available: www.htsmodelling.com
- [129] F. Liang, S. Venuturumilli, H. Zhang, M. Zhang, J. Kvitkovic, S. Pamidi, Y. Wang, and W. Yuan, "A finite element model for simulating second generation high temperature superconducting coils/stacks with large number of turns," *J. Appl. Phys.*, vol. 122, no. 4, Jul. 2017, Art. no. 043903.
- [130] M. Kapolka, E. Pardo, F. Grilli, A. Baskys, V. Climente-Alarcon, A. Dadhich, and B. A. Glowacki, "Cross-field demagnetization of stacks of tapes: 3D modelling and measurements," *Supercond. Sci. Technol.*, vol. 33, Nov. 2019, Art. no. 044019.
- [131] L. Bortot, B. Auchmann, I. C. Garcia, H. D. Gersem, M. Maciejewski, M. Mentink, S. Schops, J. V. Nugteren, and A. P. Verweij, "A coupled A-H formulation for magneto-thermal transients in high-temperature superconducting magnets," *IEEE Trans. Appl. Supercond.*, vol. 30, no. 5, Aug. 2020, Art. no. 4900911.



FRANCESCO GRILLI received the M.S. degree in physics from the University of Genoa, Genoa, Italy, in 1998, the Ph.D. degree in technical sciences from the École Polytechnique Fédérale de Lausanne, Lausanne, Switzerland, in 2004, and the Habilitation degree in superconductivity for energy applications from the Karlsruhe Institute of Technology, Karlsruhe, Germany, in 2017.

From 2004 to 2007, he was a Postdoctoral Researcher with the Los Alamos National Laboratory, Los Alamos, NM, USA. From 2007 to 2009, he was with the École Polytechnique de Montréal, Montréal, QC, Canada. Since 2009, he has been with the Karlsruhe Institute of Technology, where he is currently the Leader of the group AC Losses in High-Temperature Superconductors. He has published over 140 peer-reviewed journal articles. His main research interests include the two-dimensional and three-dimensional modeling of high-temperature superconductors and the dc and ac characterization of their properties. He is one of the first scientists in the world to develop the *H*-formulation finite-element method for the modeling of superconductors in the commercial software package COMSOL Multiphysics.

Dr. Grilli was a recipient of the 2008 and 2014 Van Duzer Prize for best contributed nonconference paper published in the IEEE TRANSACTIONS ON APPLIED SUPERCONDUCTIVITY and of the 2011 Dr. Meyer-Struckmann Science Prize for his work on numerical modeling of superconductors.



BOYANG SHEN (Member, IEEE) received the double Bachelor of Engineering (B.Eng.) (First Class Hons.) degree in electrical and electronic engineering from Cardiff University, U.K., and North China Electric Power University (NCEPU), China, in 2012, the Master of Science (M.Sc.) degree in nuclear engineering from Imperial College London, U.K., in 2013, and the Master of Philosophy (M.Phil.) degree in engineering (electrical engineering) and the Doctor of Philosophy (Ph.D.) degree in engineering (electrical engineering) from the University of Cambridge, U.K., in 2014 and 2018, respectively.

He is currently a Research Fellow with Clare Hall, and a Research Associate with the Department of Engineering, University of Cambridge. He is working with the Electrical Power and Energy Conversion (EPEC) Superconductivity Group, directed by Dr. T. Coombs. He has published more than 50 peer-reviewed journal articles. His research interests include the *H*-formulation finite-element method for the modeling of superconductors, electromagnetic characteristics and AC loss analysis of High Temperature Superconductors (HTS), and the novel design of superconducting magnets.

In 2018, he was awarded the IEEE Graduate Study Fellowship in Applied Superconductivity, which is the highest prize for graduates in the superconductivity community in the world. In 2020, he was awarded the Royal Academy of Engineering (RAEng) Engineers Trust Young Engineer of the Year, which is one of the world highest honors for the scientists and engineers who have demonstrated excellence in the early stage of their career.



TIM COOMBS (Senior Member, IEEE) received the B.A. and M.A. degrees (Hons.) in engineering science and the Ph.D. degree in superconducting magnetic bearings from the University of Cambridge, U.K., in 1983, 1987, and 1995, respectively.

He was originally appointed in 2000 as a Lecturer, and appointed as a Senior Lecturer in 2004 at the Department of Engineering, University of Cambridge. He is currently the Director of Magnifye Ltd., U.K. He is also a Fellow of Magdalene College, University of Cambridge. He is also the Head of the Electrical Power and Energy Conversion (EPEC) Group, and the Head of EPEC Superconductivity Group, University of Cambridge. He has done a great amount of useful works in several areas of superconductivity research, ranging from the novel theoretical tools for the understanding of superconducting properties up to real breakthroughs in the design of cutting-edge technologies. He is one of the first scientists in the world to develop the *H*-formulation finite-element method for the modeling of superconductors in the commercial software package COMSOL Multiphysics. He has an internationally leading publication record which extends to more than 200 articles released in peer-reviewed journals.

...