

## Space-Time Autocoding: Arbitrarily Reliable Communication in a Single Fading Interval

Thomas L. Marzetta, Bertrand Hochwald and Babak Hassibi  
 Mathematical Sciences Center  
 Lucent Technologies  
 600 Mountain Avenue  
 Murray Hill, NJ 07974  
 e-mail: {t1m, hochwald, hassibi}@research.bell-labs.com

*Abstract* — Prior treatments of space-time communications in Rayleigh flat fading generally assume that channel coding covers either one fading interval—in which case there is a nonzero “outage capacity”—or multiple fading intervals—in which case there is a nonzero Shannon capacity. However, we establish conditions under which channel codes span only one fading interval and yet are arbitrarily reliable. In short, space-time signals are their own channel codes. We call this phenomenon *space-time autocoding*, and the accompanying capacity the *space-time autocapacity*.

Let an  $M$ -transmitter-antenna,  $N$ -receiver-antenna Rayleigh flat fading channel be characterized by an  $M \times N$  matrix of independent propagation coefficients, distributed as zero-mean, unit-variance complex Gaussian random variables. This propagation matrix is unknown to the transmitter, remains constant during a  $T$ -symbol coherence interval, and there is a fixed total transmit power. Let the coherence interval and number of transmitter antennas be related as  $T = \beta M$  for some  $\beta$ . A  $T \times M$  matrix-valued signal, associated with  $R \cdot T$  bits of information for some rate  $R$  is transmitted during the  $T$ -symbol coherence interval. Then there is a positive space-time autocapacity  $C_a$  such that for all  $R < C_a$ , the block probability of error goes to zero as the pair  $(T, M) \rightarrow \infty$  such that  $T/M = \beta$ . The autocoding effect occurs whether or not the propagation matrix is known to the receiver, and  $C_a = N \log(1 + \rho)$  in either case independently of  $\beta$ , where  $\rho$  is the expected SNR at each receiver antenna. Lower bounds on the cutoff rate derived from random Unitary Space-Time signals suggest that the autocoding effect manifests itself for relatively small values of  $T$  and  $M$ . For example within a single coherence interval of duration  $T = 16$ , for  $M = 7$  transmitter antennas and  $N = 4$  receiver antennas, and an 18 dB expected SNR, a total of 80 bits (corresponding to rate  $R = 5$ ) can theoretically be transmitted with a block probability of error less than  $10^{-9}$ , all without any training or knowledge of the propagation matrix.

A complete copy of this paper is available on the web at <http://mars.bell-labs.com>.

### REFERENCES

- [1] B. Hochwald, T. Marzetta and B. Hassibi, “Space-time autocoding,” submitted to *IEEE Trans. Info. Theory*. Also Bell Labs. tech. report, Nov. 1999.