

A CHAIN RATIO EXPONENTIAL TYPE ESTIMATOR IN TWO-PHASE SAMPLING USING AUXILIARY INFORMATION

Rohini Yadav

Department of Applied Mathematics, Indian School of Mines, Dhanbad, India

Lakshmi N. Upadhyaya

Department of Applied Mathematics, Indian School of Mines, Dhanbad, India

Housila P. Singh

School of Studies in Statistics, Vikram University, Ujjain, India

S. Chatterjee

Department of Applied Mathematics, Indian School of Mines, Dhanbad, India

1. INTRODUCTION

It is a common practice to use auxiliary information at the estimation stage for increasing the efficiency of the estimators of the population mean \bar{Y} of the study variable y . Out of many ratio, regression and product methods of estimation are good examples in this context. When the population mean \bar{X} of the auxiliary variable x is known, a number of modified versions of ratio and product estimators have been proposed by various authors including Srivastava (1967), Chakraborty (1968), Gupta (1978), Vos (1980), Walsh (1970), Upadhyaya et al. (2004), Singh and Tailor (2005 a, b) and others.

In case when the population mean \bar{X} of the auxiliary variable x is not known then it is often estimated from a preliminary large sample on which only the auxiliary character x is observed. After that a small sample is drawn from preliminary large sample for estimating the study variable y . This technique is known as the two-phase or double sampling. Prasad et al. (1996), Singh and Gangele (1999), Upadhyaya et al. (2006) and many others have reported the modified ratio estimators in two phase sampling.

The two-phase sampling is effective and economical procedure to find out the reliable estimate of the unknown population mean \bar{X} of the auxiliary variable x .

Consider a finite population $U = (U_1, U_2, \dots, U_N)$ of N units. Let (y, x) be the study variable and the auxiliary variable respectively, taking values (y_i, x_i) for the

i^{th} unit U_i . Let $\bar{Y} = (1/N) \sum_{i=1}^N y_i$ and $\bar{X} = (1/N) \sum_{i=1}^N x_i$ be the population means

of study variable y and auxiliary variable x respectively.

When the population mean \bar{X} of the auxiliary variable x is known, the classical ratio estimator for population mean \bar{Y} is defined by

$$\bar{y}_r = \bar{y} \left(\frac{\bar{X}}{\bar{x}} \right); \bar{x} \neq 0 \quad (1)$$

where $\bar{y} = (1/n) \sum_{i=1}^n y_i$ and $\bar{x} = (1/n) \sum_{i=1}^n x_i$.

When the population mean \bar{X} of the auxiliary variable x is unknown, Sukhatme (1962) has defined the two-phase (or double) sampling ratio estimator of population mean \bar{Y} as

$$\bar{y}_{rd} = \bar{y} \left(\frac{\bar{x}'}{\bar{x}} \right); \bar{x} \neq 0 \quad (2)$$

where $\bar{x}' = (1/n') \sum_{i=1}^{n'} x_i$ is the sample mean of x based on first phase sample of size n' .

Suppose that the population mean \bar{Z} of the another auxiliary variable z is available which is closely related to x but compared to x remotely related to y (i.e. $\rho_{xz} > \rho_{yx}$; ρ_{xz} being the correlation coefficient between x and z).

In this situation, Chand (1975) has suggested a chain ratio-type estimator for the population mean \bar{Y} defined as

$$\bar{y}_{rd}^{(C)} = \bar{y} \left(\frac{\bar{x}'}{\bar{x}} \right) \left(\frac{\bar{Z}}{\bar{z}'} \right); \bar{x} \neq 0, \bar{z}' \neq 0 \quad (3)$$

where $\bar{z}' = (1/n') \sum_{i=1}^{n'} z_i$ is the sample mean of the second auxiliary variable z based on n' observations.

This type of situation has been briefly discussed by Kiregyera (1980, 1984) Mukherjee et al. (1987), Srivastava et al. (1989), Srivenkataramana and Tracy (1989), Upadhyaya et al. (1990), Singh and Singh (1991), Singh et al. (1994), Upadhyaya and Singh (2001), Singh et al. (2006), Singh et al. (2009) and others.

Motivated by Bahl and Tuteja (1991), Singh and Vishwakarma (2007) have suggested the ratio exponential type estimator for finite population mean \bar{Y} in two phase sampling as

$$\bar{y}_{red} = \bar{y} \exp\left(\frac{\bar{x}' - \bar{x}}{\bar{x}' + \bar{x}}\right). \quad (4)$$

To the first degree of approximation, the mean squared errors (MSEs) of the estimators \bar{y}_{rd} , $\bar{y}_{rd}^{(C)}$ and \bar{y}_{red} are respectively given by

$$MSE(\bar{y}_{rd}) = \bar{Y}^2 \left[\left(\frac{1-f}{n}\right) C_y^2 + \left(\frac{1-f''}{n}\right) C_x^2 (1-2K_{01}) \right] \quad (5)$$

$$MSE(\bar{y}_{rd}^{(C)}) = \bar{Y}^2 \left[\left(\frac{1-f}{n}\right) C_y^2 + \left(\frac{1-f'}{n'}\right) C_z^2 (1-2K_{02}) + \left(\frac{1-f''}{n}\right) C_x^2 (1-2K_{01}) \right] \quad (6)$$

$$MSE(\bar{y}_{red}) = \bar{Y}^2 \left[\left(\frac{1-f}{n}\right) C_y^2 + \frac{1}{4} \left(\frac{1-f''}{n}\right) C_x^2 (1-4K_{01}) \right] \quad (7)$$

where $f = (n/N)$, $f' = (n'/N)$, $f'' = (n/n')$ be sample fractions based on the sample of size n and n' , $C_y = (S_y/\bar{Y})$, $C_x = (S_x/\bar{X})$, $C_z = (S_z/\bar{Z})$ be the coefficient of variations of x , y and z respectively, $\rho_{yx} = (S_{yx}/S_y S_x)$ and $\rho_{yz} = (S_{yz}/S_y S_z)$ be the correlation coefficients between (y, x) and (y, z) respectively, $K_{01} = \rho_{yx} (C_y/C_x)$ and $K_{02} = \rho_{yz} (C_y/C_z)$.

This paper deals with problem of estimating the finite population mean \bar{Y} using auxiliary variables x and z in two-phase or double sampling. A family of chain ratio exponential type estimators has been proposed in two-phase (or double sampling) sampling and its properties have been discussed under large sample of approximation. Regions of preferences of the suggested class of estimators have been defined over others. An empirical study is carried out to judge the merits of the proposed class of estimators over two-phase ratio estimator \bar{y}_{rd} , Chand's (1975) estimator $\bar{y}_{rd}^{(C)}$ and Singh and Vishwakarma's (2007) estimator \bar{y}_{red} .

2. THE SUGGESTED CLASS OF ESTIMATORS

Motivated by Singh and Vishwakarma (2007), we have suggested a class of chain ratio exponential type estimators for population mean \bar{Y} using information on two auxiliary variables x and z in two-phase or double sampling as

$$\hat{t}_{red} = \bar{y} \exp \left[\frac{\frac{\hat{X}_{rd} - \bar{x}}{\hat{X}_{rd} + \bar{x}}}{\frac{\hat{X}_{rd} - \bar{x}}{\hat{X}_{rd} + \bar{x}}} \right] \quad (8)$$

where $\hat{X}_{rd} = \frac{\bar{x}'}{\left(\frac{\bar{x}'}{a\bar{z}'} + b\right)}(a\bar{Z} + b)$, 'a' and 'b' are the suitably chosen positive scalars.

Thus the proposed class of estimators can be expressed as

$$\hat{t}_{red} = \bar{y} \exp \left[\frac{\frac{\bar{x}'}{\left(\frac{\bar{x}'}{a\bar{z}'} + b\right)}(a\bar{Z} + b) - \bar{x}}{\frac{\bar{x}'}{\left(\frac{\bar{x}'}{a\bar{z}'} + b\right)}(a\bar{Z} + b) + \bar{x}} \right]. \quad (9)$$

To obtain the bias and mean squared error (MSE) of the suggested family of estimators \hat{t}_{red} , we write

$$\bar{y} = \bar{Y}(1 + e_0), \quad \bar{x} = \bar{X}(1 + e_1), \quad \bar{x}' = \bar{X}'(1 + e_2), \quad \bar{z}' = \bar{Z}'(1 + e_3)$$

such that

$$\left. \begin{aligned} E(e_0) &= E(e_1) = E(e_2) = E(e_3) = 0 \\ E(e_0^2) &= \left(\frac{1-f}{n}\right) C_y^2, & E(e_1^2) &= \left(\frac{1-f}{n}\right) C_x^2, & E(e_2^2) &= \left(\frac{1-f'}{n'}\right) C_x'^2, \\ E(e_3^2) &= \left(\frac{1-f'}{n'}\right) C_z'^2, & E(e_0 e_1) &= \left(\frac{1-f}{n}\right) \rho_{yx} C_y C_x, & E(e_0 e_2) &= \left(\frac{1-f'}{n'}\right) \rho_{yx} C_y C_x, \\ E(e_0 e_3) &= \left(\frac{1-f'}{n'}\right) \rho_{yz} C_y C_z, & E(e_1 e_2) &= \left(\frac{1-f'}{n'}\right) C_x^2, & E(e_1 e_3) &= \left(\frac{1-f'}{n'}\right) \rho_{xz} C_x C_z, \\ E(e_2 e_3) &= \left(\frac{1-f'}{n'}\right) \rho_{xz} C_x C_z \end{aligned} \right\}$$

Expressing (9) in terms of e 's we have

$$\begin{aligned}
\hat{i}_{red} &= \bar{Y}(1+e_0) \exp \left[\left\{ (1+e_2)(1+\theta_0 e_3)^{-1} - (1+e_1) \right\} \left\{ (1+e_2)(1+\theta_0 e_3)^{-1} + (1+e_1) \right\}^{-1} \right] \\
\text{where } \theta_0 &= \left(\frac{a\bar{Z}}{a\bar{Z}+b} \right). \\
&= \bar{Y}(1+e_0) \left[1 + \left\{ (1+e_2)(1+\theta_0 e_3)^{-1} - (1+e_1) \right\} \left\{ (1+e_2)(1+\theta_0 e_3)^{-1} + (1+e_1) \right\}^{-1} \right. \\
&\quad \left. + \frac{1}{2} \left\{ (1+e_2)(1+\theta_0 e_3)^{-1} - (1+e_1) \right\}^2 \left\{ (1+e_2)(1+\theta_0 e_3)^{-1} + (1+e_1) \right\}^{-2} + \dots \right] \\
&= \bar{Y}(1+e_0) \left[1 + \left\{ (1+e_2)(1-\theta_0 e_3 + \theta_0^2 e_3^2) - (1+e_1) \right\} \left\{ (1+e_2)(1-\theta_0 e_3 + \theta_0^2 e_3^2) + (1+e_1) \right\}^{-1} \right. \\
&\quad \left. + \frac{1}{2} \left\{ (1+e_2)(1-\theta_0 e_3 + \theta_0^2 e_3^2) - (1+e_1) \right\}^2 \left\{ (1+e_2)(1-\theta_0 e_3 + \theta_0^2 e_3^2) + (1+e_1) \right\}^{-2} + \dots \right] \\
&= \bar{Y}(1+e_0) \left[1 + \frac{1}{2} \left(e_2 - e_1 - \theta_0 e_3 + \frac{e_1^2}{2} - \frac{e_2^2}{2} + \frac{\theta_0^2 e_3^2}{2} \right) + \right. \\
&\quad \left. + \frac{1}{8} (e_1^2 + e_2^2 + \theta_0^2 e_3^2 - 2e_1 e_2 - 2\theta_0 e_2 e_3 + 2\theta_0 e_1 e_3) + \dots \right] \\
&= \bar{Y}(1+e_0) \left[1 - \frac{1}{2} e_1 + \frac{1}{2} e_2 - \frac{1}{2} \theta_0 e_3 + \frac{3}{8} e_1^2 - \frac{1}{8} e_2^2 + \right. \\
&\quad \left. + \frac{5}{8} \theta_0^2 e_3^2 - \frac{1}{4} e_1 e_2 - \frac{1}{4} \theta_0 e_2 e_3 + \frac{1}{4} \theta_0 e_1 e_3 + \dots \right]
\end{aligned}$$

Neglecting terms of e's having power greater than two, we have

$$\begin{aligned}
\hat{i}_{red} &\cong \bar{Y} \left[1 + e_0 - \frac{1}{2} e_1 + \frac{1}{2} e_2 - \frac{1}{2} \theta_0 e_3 + \frac{3}{8} e_1^2 - \frac{1}{8} e_2^2 + \frac{5}{8} \theta_0^2 e_3^2 - \frac{1}{2} e_0 e_1 + \frac{1}{2} e_0 e_2 \right. \\
&\quad \left. - \frac{1}{4} e_1 e_2 - \frac{1}{2} \theta_0 e_0 e_3 + \frac{1}{4} \theta_0 e_1 e_3 + \frac{1}{4} \theta_0 e_2 e_3 \right]
\end{aligned}$$

or

$$\begin{aligned}
(\hat{i}_{red} - \bar{Y}) &= \bar{Y} \left[e_0 - \frac{1}{2} e_1 + \frac{1}{2} e_2 - \frac{1}{2} \theta_0 e_3 + \frac{3}{8} e_1^2 - \frac{1}{8} e_2^2 + \frac{5}{8} \theta_0^2 e_3^2 - \frac{1}{2} e_0 e_1 + \frac{1}{2} e_0 e_2 \right. \\
&\quad \left. - \frac{1}{4} e_1 e_2 - \frac{1}{2} \theta_0 e_0 e_3 + \frac{1}{4} \theta_0 e_1 e_3 + \frac{1}{4} \theta_0 e_2 e_3 \right] \quad . \quad (10)
\end{aligned}$$

Taking expectation of both sides of (10), we get the bias of the estimator \hat{i}_{red} to the first degree of approximation is given by

$$B(\hat{t}_{red}) = \bar{Y} \left[\frac{1}{2} \left(\frac{1-f}{n} \right) C_x^2 \left(\frac{3}{4} - K_{01} \right) - \frac{1}{2} \left(\frac{1-f'}{n'} \right) \left(\frac{3}{4} C_x^2 - \frac{5}{4} \theta_0^2 C_{\tilde{x}}^2 - \rho_{yx} C_y C_x + \theta_0 \rho_{y\tilde{x}} C_y C_{\tilde{x}} - \theta_0 \rho_{x\tilde{x}} C_x C_{\tilde{x}} \right) \right] \quad (11)$$

Squaring both sides of (10) and neglecting terms of e 's having power greater than two, we have

$$\begin{aligned} (\hat{t}_{red} - \bar{Y})^2 &\cong \bar{Y}^2 \left(e_0 - \frac{e_1}{2} + \frac{e_2}{2} - \frac{\theta_0 e_3}{2} \right)^2 \\ &= \bar{Y}^2 \left[e_0^2 - (e_0 e_1 - e_0 e_2 + \theta_0 e_0 e_3) + \right. \\ &\quad \left. + \frac{1}{4} (e_1^2 + e_2^2 + \theta_0^2 e_3^2) - \frac{1}{2} (e_1 e_2 - \theta_0 e_1 e_3 + \theta_0 e_2 e_3) \right] \end{aligned} \quad (12)$$

Taking expectation of both sides of (12), we get the MSE of \hat{t}_{red} to the first degree of approximation as

$$\begin{aligned} MSE(\hat{t}_{red}) &= \bar{Y}^2 \left[\left(\frac{1-f}{n} \right) C_y^2 + \frac{\theta_0}{4} \left(\frac{1-f'}{n'} \right) C_{\tilde{x}}^2 (\theta_0 - 4K_{02}) + \right. \\ &\quad \left. + \frac{1}{4} \left(\frac{1-f''}{n} \right) C_x^2 (1 - 4K_{01}) \right] \end{aligned} \quad (13)$$

The MSE of \hat{t}_{red} at (13) is minimized for

$$\theta_0 = \left(\frac{2\rho_{y\tilde{x}} C_y C_{\tilde{x}}}{C_{\tilde{x}}^2} \right) = 2K_{02} = \theta_0^* \quad (\text{say}) \quad (14)$$

Thus the resulting minimum MSE of \hat{t}_{red} is given by

$$\min MSE(t) = \bar{Y}^2 \left[\left(\frac{1-f}{n} \right) C_y^2 + \frac{1}{4} \left(\frac{1-f''}{n} \right) C_x^2 (1 - 4K_{01}) - \left(\frac{1-f'}{n'} \right) \rho_{y\tilde{x}}^2 C_y^2 \right] \quad (15)$$

3. EFFICIENCY COMPARISON

3.1. When the scalar θ_0 does not coincide with its exact optimum value θ_0^*

From (5), (6), (7) and (13), we have

$$(i) \quad \begin{aligned} &MSE(\hat{t}_{rd}) - MSE(\bar{y}_{rd}) < 0 \quad \text{if} \\ &\left. \begin{aligned} &\text{either } L_1 < \theta < L_2 \\ &\text{or } L_2 < \theta < L_1 \end{aligned} \right\} \end{aligned} \tag{16}$$

$$\text{or equivalently, } \min(L_1, L_2) < \theta < \max(L_1, L_2), \tag{17}$$

$$\text{where } L_1 = \left[2K_{02} - \left(\frac{n'}{1-f'} \right) \sqrt{4 \left(\frac{1-f'}{n'} \right)^2 K_{02}^2 + \left(\frac{1-f'}{n'} \right) \left(\frac{1-f''}{n} \right) \frac{C_x^2}{C_z^2} (3-4K_{01})} \right]$$

$$\text{and } L_2 = \left[2K_{02} + \left(\frac{n'}{1-f'} \right) \sqrt{4 \left(\frac{1-f'}{n'} \right)^2 K_{02}^2 + \left(\frac{1-f'}{n'} \right) \left(\frac{1-f''}{n} \right) \frac{C_x^2}{C_z^2} (3-4K_{01})} \right].$$

$$(ii) \quad \begin{aligned} &MSE(\hat{t}_{rd}) - MSE(\bar{y}_{rd}^{(C)}) < 0 \quad \text{if} \\ &\left. \begin{aligned} &\text{either } L_1^* < \theta < L_2^* \\ &\text{or } L_2^* < \theta < L_1^* \end{aligned} \right\} \end{aligned} \tag{18}$$

$$\text{or equivalently, } \min(L_1^*, L_2^*) < \theta < \max(L_1^*, L_2^*), \tag{19}$$

where

$$L_1^* = \left[2K_{02} - 2 \left(\frac{n'}{1-f'} \right) \sqrt{\left(\frac{1-f'}{n'} \right)^2 (1-K_{02})^2 + \frac{1}{4} \left(\frac{1-f'}{n'} \right) \left(\frac{1-f''}{n} \right) \frac{C_x^2}{C_z^2} (3-4K_{01})} \right]$$

and

$$L_2^* = \left[2K_{02} + 2 \left(\frac{n'}{1-f'} \right) \sqrt{\left(\frac{1-f'}{n'} \right)^2 (1-K_{02})^2 + \frac{1}{4} \left(\frac{1-f'}{n'} \right) \left(\frac{1-f''}{n} \right) \frac{C_x^2}{C_z^2} (3-4K_{01})} \right]$$

$$(iii) \quad \begin{aligned} &MSE(\hat{t}_{rd}) - MSE(\bar{y}_{rd}) < 0 \quad \text{if} \\ &\left. \begin{aligned} &\text{either } 0 < \theta < 4K_{02} \\ &\text{or } 4K_{02} < \theta < 0 \end{aligned} \right\} \end{aligned} \tag{20}$$

$$\text{or equivalently, } \min(0, 4K_{02}) < \theta < \max(0, 4K_{02}). \quad (21)$$

3.2. When the scalar θ_0 exactly coincides with its true optimum value θ_0^*

From (5), (6), (7) and (15), we get

$$(iv) \quad \min MSE(\hat{t}_{red}) - MSE(\bar{y}_{red}) < 0 \quad \text{if} \quad (22)$$

$$\left\{ \left(\frac{1-f''}{n} \right) (4K_{01} - 3) C_x^2 - 4 \left(\frac{1-f'}{n'} \right) \rho_{yz}^2 C_y^2 \right\} < 0$$

$$\text{which is always satisfied as long as } K_{01} < (3/4) \quad (23)$$

$$(v) \quad \min MSE(\hat{t}_{red}) - MSE(\bar{y}_{red}^{(C)}) < 0 \quad \text{if} \quad (24)$$

$$\left\{ \left(\frac{1-f''}{n} \right) (4K_{01} - 3) C_x^2 - 4 \left(\frac{1-f'}{n'} \right) C_x^2 (1 - K_{02})^2 \right\} < 0$$

$$\text{which is always true if } K_{01} < (3/4) \quad (25)$$

$$(vi) \quad \min MSE(\hat{t}_{red}) - MSE(\bar{y}_{red}) < 0 \quad \text{if} \quad (26)$$

$$= \left(\frac{1-f'}{n'} \right) \rho_{yz}^2 C_y^2 > 0$$

$$\rho_{yz} > 0.$$

Thus if the correlation between y and z is positive, the proposed class of estimators \hat{t}_{red} (at optimum) is always better than the estimator \bar{y}_{red} due to Singh and Vishwakarma (2007).

4. EMPIRICAL STUDY

To judge the merits of the proposed class of estimators \hat{t}_{red} over the two-phase ratio estimator \bar{y}_{red} , Chand's (1975) chain ratio type estimator $\bar{y}_{red}^{(C)}$ and Singh and Vishwakarma's (2007) estimator \bar{y}_{red} , we have taken the four natural population data sets. The parameters of the populations are defined below:

Population I [Source: Anderson (1958), pp.97]

The variables are

y: Head length of second son

x: Head length of first son

z: Head breadth of first son

$$N = 25, \quad n' = 10, \quad n = 7, \quad \bar{Y} = 183.84, \quad \bar{X} = 185.72,$$

$$\bar{Z} = 151.12, \quad C_y = 0.0546, \quad C_x = 0.0526, \quad C_z = 0.0488, \quad \rho_{yx} = 0.7108,$$

$$\rho_{yz} = 0.6932, \quad \rho_{xz} = 0.7346.$$

Population II [Source: Singh (1967)]

The variables are

y: Number of females employed

x: Number of females in service

z: Number of educated females

$$N = 61, \quad n' = 20, \quad n = 10, \quad \bar{Y} = 7.46, \quad \bar{X} = 5.31,$$

$$\bar{Z} = 179.00, \quad C_y = 0.7103, \quad C_x = 0.7587, \quad C_z = 0.2515, \quad \rho_{yx} = 0.7737,$$

$$\rho_{yz} = -0.2070, \quad \rho_{xz} = -0.0033.$$

Population III [Source: Murthy (1967) pp.226]

The variables are

y: Output

x: Number of workers

z: Fixed capital

$$N = 80, \quad n' = 25, \quad n = 10, \quad \bar{Y} = 5182.638, \quad \bar{X} = 283.875,$$

$$\bar{Z} = 1126.00, \quad C_y = 0.3520, \quad C_x = 0.9430, \quad C_z = 0.7460, \quad \rho_{yx} = 0.9136,$$

$$\rho_{yz} = 0.9413, \quad \rho_{xz} = 0.9859.$$

Population IV [Source: Cochran (1977)]

The variables are

y: Number of ‘placebo’ children.

x: Number of paralytic polio cases in the placebo group.

z: Number of paralytic polio cases in the ‘not inoculated’ group.

$$N = 34, \quad n' = 15, \quad n = 10, \quad \bar{Y} = 4.92, \quad \bar{X} = 2.59,$$

$$\bar{Z} = 2.91, \quad C_y = 1.0123, \quad C_x = 1.2318, \quad C_z = 1.0720, \quad \rho_{yx} = 0.7326,$$

$$\rho_{yz} = 0.6430, \quad \rho_{xz} = 0.6837.$$

For the purpose of efficiency comparison of the estimators \bar{y}_{rd} , $\bar{y}_{rd}^{(C)}$, \bar{y}_{red} and the proposed class of estimators \hat{t}_{red} over the usual sample mean estimator \bar{y} , we have computed the percent relative efficiencies (PREs) of the estimators w.r.t \bar{y} using the formula:

$$PRE(., \bar{y}) = \frac{MSE(\bar{y})}{MSE(.)} \times 100; \quad \text{where } (.) = \bar{y}, \bar{y}_{rd}, \bar{y}_{rd}^{(C)}, \bar{y}_{red} \text{ and } \hat{t}_{red}.$$

Findings are given in the Table 1.

TABLE 1
PREs of the estimators \bar{y} , \bar{y}_{rd} , $\bar{y}_{rd}^{(C)}$, \bar{y}_{red} and \hat{t}_{red} with respect to \bar{y}

S. No.	Estimator	PRE(., \bar{y})			
		Population I	Population II	Population III	Population IV
1.	\bar{y}	100.00	100.00	100.00	100.00
2.	\bar{y}_{rd}	122.5362	144.1780	38.8489	116.6397
3.	$\bar{y}_{rd}^{(C)}$	178.8180	124.5562	36.6101	137.0018
4.	\bar{y}_{red}	123.2272	147.7192	180.6020	132.7205
5.	\hat{t}_{red}	188.3079	151.4388	364.8648	187.0466

From Table 1, it is observed that the proposed class of estimators \hat{t}_{red} is more efficient than the sample mean estimator \bar{y} , two-phase ratio estimator \bar{y}_{rd} , Chand’s (1975) chain ratio estimator $\bar{y}_{rd}^{(C)}$ and Singh and Vishwakarma’s (2007) estimator \bar{y}_{red} for the given data sets.

5. CONCLUSION

In this paper, we have suggested a class of chain ratio exponential type estimators in two-phase sampling. Its bias and mean squared error (MSE) are obtained upto the first degree of approximation. Theoretically, it has shown that both the proposed class of estimators \hat{t}_{red} and asymptotic optimum estimator (AOE) in class of estimators \hat{t}_{red} are more efficient than the two-phase ratio estimator \bar{y}_{rd} , Chand's (1975) chain-type estimator $\bar{y}_{rd}^{(C)}$ and Singh and Vishwakarma's (2007) estimator \bar{y}_{rd} in double sampling scheme under some realistic conditions. In support of the proposed class of estimators, an empirical study is carried out. It is observed that the suggested class of estimators \hat{t}_{red} is more precise than the usual unbiased estimator \bar{y} , two-phase ratio estimator \bar{y}_{rd} , Chand's (1975) chain-type estimator $\bar{y}_{rd}^{(C)}$ and Singh and Vishwakarma's (2007) estimator \bar{y}_{rd} . Thus we recommended our study for its use in practice.

ACKNOWLEDGEMENTS

Authors are thankful to the editor-in-chief and unknown learned referees for their valuable suggestions/comments on earlier draft of the paper. The authors acknowledge the University Grants Commission, New Delhi, India for financial support in the project number F. No. 34-137/2008(SR). The authors are also thankful to Indian School of Mines, Dhanbad and Vikram University, Ujjain for providing the facilities to carry out the research work.

REFERENCES

- T. W. ANDERSON (1958), *An Introduction to Multivariate Statistical Analysis*. John Wiley & Sons, Inc., New York.
- S. BAHL AND R.K. TUTEJA (1991), *Ratio and product type exponential estimator*. Information and Optimization Sciences, 12, pp. 159-163.
- R.P. CHAKRABORTY (1968), *Contribution to the theory of ratio-type estimators*, Ph.D. Thesis, Texas A and M University, U.S.A.
- L. CHAND (1975), *Some ratio type estimators based on two or more auxiliary variables*. Unpublished Ph. D. thesis, Iowa State University, Ames, Iowa (USA).
- W.G. COCHRAN (1977), *Sampling techniques*. John Wiley & Sons, New York.
- B. KIREGYERA (1980), *A chain ratio-type estimator in finite population double sampling using two auxiliary variables*, *Metrika*, 27, pp.217-223.

- B. KIREGYERA (1984), *Regression-type estimators using two auxiliary variables and the model of double sampling from finite populations*, *Metrika*, 31, pp. 215-226.
- P.C. GUPTA (1978), *On some quadratic and higher degree ratio and product estimators*, *Journal of Indian Society of Agricultural Statistics*, 30, no. 2, pp. 71-80.
- H.P. SINGH, N. MATHUR AND P. CHANDRA (2009), *A chain-type estimator for population variance using two auxiliary variables in two-phase sampling*. *Statistics in Transition-new series*, 10, no. 1, pp. 75-84.
- H. P. SINGH, S. SINGH AND J.M. KIM (2006), *General families of chain ratio type estimators of the population mean with known coefficient of variation of the second auxiliary variable in two phase sampling*, *Journal of the Korean Statistical Society*, 35, no. 4, pp. 377-395.
- R. MUKHERJEE, T.J. RAO AND K. VIJAYAN (1987), *Regression type estimators using multiple auxiliary information*, *Aust. Journ. Stat.*, 29, no. 3, pp. 244-254.
- M.N. MURTHY (1967), *Sampling Theory and Methods*, Statistical Publishing Society, Calcutta, India.
- B. PRASAD, R.S. SINGH AND H.P. SINGH (1996), *Some chain ratio type estimators for ratio of two population means using two auxiliary characters in two phase sampling*, *Metron*, LIV, no. 1-2, pp. 95-113.
- H.P. SINGH AND R.K. GANGELE (1999), *Classes of almost unbiased ratio and product-type estimators in two phase sampling*, *Statistica*, LIX, no. 1, pp. 109-124.
- H.P. SINGH AND R. TAILOR (2005 a), *Estimation of finite population mean with known coefficient of variation of an auxiliary character*, *Statistica*, LXV, no. 3, pp. 301-313.
- H.P. SINGH AND R. TAILOR (2005 b), *Estimation of finite population mean using known correlation coefficient between auxiliary characters*, *Statistica*, LXV, no. 4, pp. 407-418.
- H.P. SINGH AND G.K. VISHWAKARMA (2007), *Modified exponential ratio and product estimators for finite population mean in double sampling*, *Austrian Journal of Statistics*, 36, no. 3, pp. 217-225.
- M.P. SINGH (1967), *Ratio-cum-product method of estimation*, *Metrika*, 12, pp. 34-42.
- V.K. SINGH AND G.N. SINGH (1991), *Chain type regression estimators with two auxiliary variables under double sampling scheme*, *Metron*, 49, pp. 279-289.
- V.K. SINGH, HARI P. SINGH, HOUSILA P. SINGH AND D. SHUKLA (1994), *A general class of chain estimators for ratio and product of two means of a finite population*, *Communication in Statistics Theory & Method*, 23, no. 5, pp. 1341-1355.

S.K. SRIVASTAVA (1967), *An estimator using auxiliary information in sample surveys*, Calcutta Statistical Association Bulletin, 16, pp. 121-132.

S.R. SRIVASTAVA, S.R. SRIVASTAVA AND B.B. KHARE (1989), *Chain ratio type estimator for ratio of two population means using auxiliary characters*, Communication in Statistics Theory & Method, 18, pp. 3917-3926.

T. SRIVENKATARAMANA AND D.S. TRACY (1989), *Two phase sampling for selection with probability proportional to size in sample surveys*, Biometrika, 76, pp. 818-821.

B.V. SUKHATME (1962), *Some ratio-type estimators in two-phase sampling*, Journal of the American Statistical Association, 57, pp. 628-632.

L.N. UPADHYAYA AND G.N. SINGH (2001), *Chain type estimators using transformed auxiliary variable in two-phase sampling*, Advances in Modeling and Analysis, 38, no. 1-2, pp. 1-10.

L.N. UPADHYAYA, K.S. KUSHWAHA AND H.P. SINGH (1990), *A modified chain ratio type estimator in two-phase sampling using multi-auxiliary information*, Metron, 48, pp. 381-393.

L.N. UPADHYAYA, H.P. SINGH AND S. SINGH (2004), *A family of almost unbiased estimators for negatively correlated variables using Jackknife Technique*, Statistica, LXIV, 4, pp. 767-778.

L.N. UPADHYAYA, H.P. SINGH AND R. TAILOR (2006), *Estimation of mean with known coefficient of variation of an auxiliary variable in two phase sample*, Statistics in Transition, 7, no. 6, pp. 1327-1344.

J.W.E. VOS (1980), *Mixing of direct, ratio and product method estimators*, Statist. Neerl., 34, pp. 209-218.

J.E. WALSH (1970), *Generalization of ratio estimate for population total*, Sankhya, A, 32, pp. 99-106.

SUMMARY

A chain ratio exponential type estimator in two-phase sampling using auxiliary information

This paper advocates the problem of estimating the population mean \bar{Y} of the study variable y using the information on two auxiliary variables x and z . We have suggested the family of chain ratio exponential type estimators in two-phase (or double) sampling. The bias and mean squared error (MSE) are obtained upto the first order of approximation. The suggested class of estimators is more efficient than the two-phase ratio estimator \bar{y}_{rd} , Chand's (1975) chain-type ratio estimator $\bar{y}_{rd}^{(C)}$ and Singh and

Vishwakarma's (2007) estimator \bar{y}_{rd} in two-phase (or double) sampling. An empirical study is given to justify the superiority of the proposed estimator.